

# GXW4216 V2/GXW4224 V2/GXW4232 V2/GXW4248 V2

## Firmware Release Notes

### IMPORTANT UPGRADING NOTE

- Once the GXW42xx V2 device is upgraded to 1.0.7.2, it cannot be downgraded to 1.0.5.4 or an earlier version due to the addition of 2nd generation individual certificates.
- GXW42xx V2 device uses a different firmware file from the GXW42xx V1 device. Please use the correct firmware file for V1 and V2 devices. To distinguish GXW42xx V2 device from V1 device, please check the label on the back of the device.
  - (1) GXW42xx V2 has "V2" printed for model name. For example, "Model: GXW4216 V2". If the model's name doesn't have V1 or V2 printed, the device is GXW42xx V1.
  - (2) GXW42xx V2 has the device password printed on the label. GXW42xx V1 does not have it.
- For GXW42xx V2 device on 1.0.1.4 or earlier version to upgrade to 1.0.3.4+, the HTTP firmware upgrade path is:  
[firmware.grandstream.com/GXW42xx V2 1.0.3.9 for fw 1.0.1.4 or lower](http://firmware.grandstream.com/GXW42xx_V2_1.0.3.9_for_fw_1.0.1.4_or_lower)  
  
After upgrading to 1.0.3.9, you can upgrade to latest firmware using HTTP firmware path:  
[firmware.grandstream.com](http://firmware.grandstream.com)
- For devices on firmware 1.0.1.4 or earlier, please use file "gxw42xxfw.v2.bin" to upgrade.
- For devices on firmware 1.0.3.1 or higher, please use file "gxw42xxv2fw.bin" to upgrade.
- Once the GXW42xx V2 device is upgraded to 1.0.3.x, it cannot be downgraded to 1.0.2 x or earlier version.

## Table of Content

<b>IMPORTANT UPGRADING NOTE .....</b>	<b>1</b>
<b>FIRMWARE VERSION 1.0.27.3 .....</b>	<b>6</b>
PRODUCT NAME .....	6
DATE .....	6
FIRMWARE FILE INFORMATION .....	6
ENHANCEMENT .....	6
BUG FIX .....	7
NEW FEATURES OVERVIEW.....	7
<i>Switch SIP Server When Keep-Alive Max Lost Is Reached .....</i>	<i>7</i>
<i>Conference Notification Tone.....</i>	<i>8</i>
<i>Remote On Hold Tone .....</i>	<i>8</i>
<i>Ringing Transfer.....</i>	<i>8</i>
<i>RTP/RTCP Keep Alive On Hold.....</i>	<i>9</i>
<i>OpenVPN Username/Password .....</i>	<i>9</i>
<i>Static DNS.....</i>	<i>10</i>
<i>Strict Password Rules .....</i>	<i>20</i>
<i>Secondary NTP server .....</i>	<i>21</i>
<i>Local Time .....</i>	<i>21</i>
<i>T.38 Max Bit Rate.....</i>	<i>22</i>
<b>FIRMWARE VERSION 1.0.25.2 .....</b>	<b>23</b>
PRODUCT NAME .....	23
DATE .....	23
FIRMWARE FILE INFORMATION .....	23
ENHANCEMENT .....	23
BUG FIX .....	23
<b>FIRMWARE VERSION 1.0.25.1 .....</b>	<b>24</b>
PRODUCT NAME .....	24
DATE .....	24
FIRMWARE FILE INFORMATION .....	24
ENHANCEMENT .....	24
BUG FIX .....	24
<b>FIRMWARE VERSION 1.0.23.2 .....</b>	<b>25</b>
PRODUCT NAME .....	25

DATE .....	25
FIRMWARE FILE INFORMATION .....	25
ENHANCEMENT.....	25
BUG FIX .....	25
NEW FEATURES OVERVIEW.....	25
<i>Keep Security Setting After Reset.....</i>	26
<b>FIRMWARE VERSION 1.0.21.2 .....</b>	<b>27</b>
PRODUCT NAME .....	27
DATE .....	27
FIRMWARE FILE INFORMATION .....	27
ENHANCEMENT.....	27
BUG FIX .....	27
<b>FIRMWARE VERSION 1.0.19.1 .....</b>	<b>28</b>
PRODUCT NAME .....	28
DATE .....	28
FIRMWARE FILE INFORMATION .....	28
ENHANCEMENT.....	28
BUG FIX .....	30
NEW FEATURES OVERVIEW.....	31
<i>AVS DTMF Detector Parameters.....</i>	31
<i>Use P-Early-Media Header.....</i>	32
<i>Ringback Tone at No Early Media.....</i>	32
<i>Radius Auth Protocol.....</i>	33
<i>Port Lock Code.....</i>	33
<i>Lock/Unlock Extension Code.....</i>	34
<b>FIRMWARE VERSION 1.0.17.1 .....</b>	<b>35</b>
PRODUCT NAME .....	35
DATE .....	35
FIRMWARE FILE INFORMATION .....	35
ENHANCEMENT.....	36
BUG FIX .....	36
NEW FEATURES OVERVIEW.....	36
<i>Replace the beginning '+' in Caller ID with.....</i>	36
<b>FIRMWARE VERSION 1.0.15.2 .....</b>	<b>37</b>
PRODUCT NAME .....	37
DATE .....	37
FIRMWARE FILE INFORMATION .....	37

ENHANCEMENT.....	38
BUG FIX .....	38
NEW FEATURES OVERVIEW.....	38
<i>Custom DTMF InBand Duration</i> .....	38
<b>FIRMWARE VERSION 1.0.13.2 .....</b>	<b>39</b>
PRODUCT NAME .....	39
DATE .....	39
FIRMWARE FILE INFORMATION .....	39
ENHANCEMENT.....	40
BUG FIX .....	40
NEW FEATURES OVERVIEW.....	40
<i>MWI Tone</i> .....	40
<i>Special Proceed Indication Tone</i> .....	41
<i>Special Condition Tone</i> .....	41
<i>Ignore Alert-Info Header</i> .....	42
<b>FIRMWARE VERSION 1.0.11.2 .....</b>	<b>44</b>
PRODUCT NAME .....	44
DATE .....	44
FIRMWARE FILE INFORMATION .....	44
ENHANCEMENT.....	44
BUG FIX .....	44
NEW FEATURES OVERVIEW.....	45
<i>Download and Process All Available Config Files</i> .....	45
<b>FIRMWARE VERSION 1.0.9.1 .....</b>	<b>46</b>
PRODUCT NAME .....	46
DATE .....	46
FIRMWARE FILE INFORMATION .....	46
ENHANCEMENT.....	46
BUG FIX .....	46
<b>FIRMWARE VERSION 1.0.7.2.....</b>	<b>47</b>
PRODUCT NAME .....	47
DATE .....	47
FIRMWARE FILE INFORMATION .....	47
ENHANCEMENT.....	47
BUG FIX .....	47
NEW FEATURES OVERVIEW.....	48
<i>Configuration File Types Allowed</i> .....	48

<i>Additional Override DHCP Option</i> .....	48
<i>SRTP Key Length</i> .....	49
<i>With Secret Key Information</i> .....	49
<i>Security Controls for SSH Access</i> .....	50
<i>Enable using tags in URL</i> .....	51

## **FIRMWARE VERSION 1.0.5.4 .....52**

PRODUCT NAME .....	52
DATE .....	52
FIRMWARE FILE INFORMATION .....	52
ENHANCEMENT .....	52
BUG FIX .....	52
NEW FEATURES OVERVIEW.....	53
<i>Enable SNMP Through Management Interface</i> .....	53
<i>Enable Syslog Through Management Interface</i> .....	53

## **FIRMWARE VERSION 1.0.3.9 .....55**

PRODUCT NAME .....	55
DATE .....	55
FIRMWARE FILE INFORMATION .....	55
BUG FIX .....	55

## **FIRMWARE VERSION 1.0.3.4 .....56**

PRODUCT NAME .....	56
DATE .....	56
FIRMWARE FILE INFORMATION .....	56
ENHANCEMENT .....	56

## FIRMWARE VERSION 1.0.27.3

### PRODUCT NAME

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### DATE

10/03/2024

### FIRMWARE FILE INFORMATION

- GXW4216 V2 firmware file name: gxw4216v2fw.bin  
MD5: 954ac073c0331f119b6140c629ada415
- GXW4224 V2 firmware file name: gxw4224v2fw.bin  
MD5: 99ed18991ad2fb6eb73467cf98e5a45d
- GXW4232 V2 firmware file name: gxw4232v2fw.bin  
MD5: cf66dfebba42c0ed7afcc9cda5aa802
- GXV4248 V2 firmware file name: gxw4248v2fw.bin  
MD5: 034eafd51f3870d82f2ad1c7b0738119

### ENHANCEMENT

- Added support to Enable/Disable WEB access through the IVR.
- Added support for the “Switch SIP Server When Keep-Alive Max Lost Is Reached”.
- [Switch SIP Server When Keep-Alive Max Lost Is Reached]
- Added support Conference Notification Tone. [Conference Notification Tone]
- Added support Remote On Hold Tone. [Remote On Hold Tone]
- Added support for Ringing Transfer. [Ringing Transfer]
- Added RTCP keep alive feature. [RTP/RTCP Keep Alive On Hold]
- Added ability to support Authentication based on Username/Password on OpenVPN. [OpenVPN Username/Password]
- Added support to configure static DNS SRV records. [Static DNS]
- Removed the complex admin password requirements.
- Added support for the Strict Password Rules. [Strict Password Rules]
- Added support Add XMPP-based connection request.
- Added support for the secondary NTP server. [Secondary NTP server]
- Added ability to set local date and time. [Local Time]
- Added support to setting the T.38 Max Bit Rate. [T.38 Max Bit Rate].

- Update the “SIP Registration Failure Retry Wait Time upon 403 Forbidden” max values to 10080 minutes.
- Added support to save syslog settings and internal logs across a factory reset.  
 P82307 Syslog Setting and Internal Logs Protection. (0- No, 1- Yes. The default is 0. Check the config template for details).

## BUG FIX

- Fixed device couldn't failover to secondary sip server when the shorter timer is set up.
- Fixed a DTMF transmission failure issue.
- Fixed device syslog has no timestamp sometimes when using Audio Codes syslog viewer.
- Fixed sends RTP/AVP in the 200 OK over SRTP outbound calls.
- Fixed an issue making the call get ended by the server after 30 mins on hold.
- Fixed a bug that caused an Inbound SRTP call to fail with "488 Not Acceptable Here" due to an index value of 88 used by Netsapiens.
- Fixed a Registration spamming issue.
- Fixed device does not show the Port extension number and values when downloading the MIB from SNMP.
- Fixed device in a probability of fax failure occurs when using UCM and PSTN at T38.
- Fixed unit can't establish SRTP Session after re-invite.
- Fixed WebUI getting slow after uploading custom Certificate Authority(CA).

## NEW FEATURES OVERVIEW

This section lists major new features and describes how to use them from the user's point of view.

### Switch SIP Server When Keep-Alive Max Lost Is Reached

- **Web Configuration**

Users can find the configuration section in Web -> Profile -> Call Settings.



The screenshot shows a configuration form with the following elements:

- A text input field labeled "ive Max Lost" with a value of "3".
- A radio button selection for "Switch SIP Server When Keep-Alive Max Lost Is Reached", with "No" selected.
- A text input field labeled "Local SIP Port" with a value of "5060".

- **Functionality**

This feature allows users to configure Switch SIP Server When Keep-Alive Max Lost Is Reached. If set to "Yes", the SIP extension will switch SIP server immediately when max lost packets of SIP OPTIONS/NOTIFY keep-alive is reached.

Pvalue	Description	Value Range	Default
28907	Switch SIP Server When Keep-Alive Max Lost Is Reached	Number:	0 - No
28908		0 - No	
28909		1 - Yes	
28910			

### Conference Notification Tone

- **Web Configuration**

Users can find the configuration section in Web -> Advanced Settings -> Ring Tones.

<b>Conference Party Hangup Tone</b>	<input type="text" value="f1=425@-15,c=600/600;"/>
<b>Conference Notification Tone</b>	<input type="text"/>
<b>Special Proceed Indication Tone</b>	<input type="text" value="f1=350@-13, f2=440@-13, c=750/750-0/0;"/>

- **Functionality**

This feature allows users to configure the Conference Notification Tone.

Pvalue	Description	Value Range	Default
7077	Conference Notification Tone	String: MaxLength is 256 Characters	(Null)

### Remote On Hold Tone

- **Web Configuration**

Users can find the configuration section in Web -> Advanced Settings -> Ring Tones.

<b>Special Condition Tone</b>	<input type="text" value="f1=350@-13, f2=450@-13, c=750/750;"/>
<b>Remote On Hold Tone</b>	<input type="text"/>

- **Functionality**

This feature allows users to configure the Remote On Hold Tone

Pvalue	Description	Value Range	Default
28858	Remote On Hold Tone	String: MaxLength is 256 Characters	(Null)

### Ringling Transfer

- **Web Configuration**

Users can find the configuration section in Web -> Profile -> Call Settings.



**Transfer on Conference Hangup**     No  Yes

**Ringing Transfer**     No  Yes

**Send Hook Flash Event**     No  Yes

- **Functionality**

This feature allows users to configure the Ringing Transfer. It defines whether the call is transferred to the other party When the transferring party hangs up while listening to the ringback tone.

Pvalue	Description	Value Range	Default
4820	Ringing Transfer	Number:	0 - No
4821		0 - No	
4822		1 - Yes	
4823			

### RTP/RTCP Keep Alive On Hold

- **Web Configuration**

Users can find the configuration section in Web -> Profile-> Call Settings



- **Functionality**

This feature allows users to configure the RTP/RTCP Keep Alive On Hold, If yes, continue to send RTP/RTCP packets to keep alive when the call is on hold.

Pvalue	Description	Value Range	Default
28839	RTP/RTCP Keep Alive On Hold	Number:	
28840		0 – No	0 – No
28841		1 – Yes	
28842			

### OpenVPN Username/Password

- **Web Configuration**

User can find the configuration section in Web -> Maintenance-> VPN.

**OpenVPN Digest**

**OpenVPN Username**

**OpenVPN Password**

**OpenVPN CA**

- **Functionality**

Configures OpenVPN authentication username and password.

Pvalue	Description	Value Range	Default
8394	OpenVPN Username	String: Maxlength is 32 Characters	(Null)
8395	OpenVPN Password	String: Maxlength is 32 Characters	(Null)

#### Static DNS

- **Web Configuration**

- Users can find the configuration in Web UI -> Advanced Settings -> Static DNS

## A Record Settings

No	Name	TTL	Address
1	<input type="text"/>	300	<input type="text"/>
2	<input type="text"/>	300	<input type="text"/>
3	<input type="text"/>	300	<input type="text"/>
4	<input type="text"/>	300	<input type="text"/>
5	<input type="text"/>	300	<input type="text"/>
6	<input type="text"/>	300	<input type="text"/>
7	<input type="text"/>	300	<input type="text"/>
8	<input type="text"/>	300	<input type="text"/>
9	<input type="text"/>	300	<input type="text"/>
10	<input type="text"/>	300	<input type="text"/>
11	<input type="text"/>	300	<input type="text"/>
12	<input type="text"/>	300	<input type="text"/>
13	<input type="text"/>	300	<input type="text"/>
14	<input type="text"/>	300	<input type="text"/>
15	<input type="text"/>	300	<input type="text"/>
16	<input type="text"/>	300	<input type="text"/>
17	<input type="text"/>	300	<input type="text"/>
18	<input type="text"/>	300	<input type="text"/>

## SRV Settings

No	Name	TTL	Priority	Weight	Port	Target
1	<input type="text"/>	300	0	0	0	<input type="text"/>
2	<input type="text"/>	300	0	0	0	<input type="text"/>
3	<input type="text"/>	300	0	0	0	<input type="text"/>
4	<input type="text"/>	300	0	0	0	<input type="text"/>
5	<input type="text"/>	300	0	0	0	<input type="text"/>
6	<input type="text"/>	300	0	0	0	<input type="text"/>
7	<input type="text"/>	300	0	0	0	<input type="text"/>
8	<input type="text"/>	300	0	0	0	<input type="text"/>
9	<input type="text"/>	300	0	0	0	<input type="text"/>
10	<input type="text"/>	300	0	0	0	<input type="text"/>
11	<input type="text"/>	300	0	0	0	<input type="text"/>
12	<input type="text"/>	300	0	0	0	<input type="text"/>
13	<input type="text"/>	300	0	0	0	<input type="text"/>
14	<input type="text"/>	300	0	0	0	<input type="text"/>
15	<input type="text"/>	300	0	0	0	<input type="text"/>
16	<input type="text"/>	300	0	0	0	<input type="text"/>
17	<input type="text"/>	300	0	0	0	<input type="text"/>
18	<input type="text"/>	300	0	0	0	<input type="text"/>

## NAPTR Settings

No	Name	TTL	Order	Preference Flags	Service	Regexp	Replacement
1	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
2	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
3	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
4	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
5	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
6	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
7	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
8	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
9	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
10	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
11	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
12	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
13	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
14	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
15	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
16	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
17	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>
18	<input type="text"/>	300	0	0	<input type="text"/>	<input type="text"/>	<input type="text"/>

- **Functionality**

This feature could let the user configure the Order Name, TTL, Order, Preference, Flags, Service, Regexp, Replacement, Priority, Weight, Target, Port, Target, and IP Address for different DNS modes in A Record, NAPTR, SRV, and Settings,

**New P Values**

**A Record Settings**

Pvalue	Description	Value range	Default
93014 93034 93054 93074 93094 93114 93134 93154 93174 93194 93214 93234 93254 93274 93294 93314 93334 93354	Name	String: Max length is 512 Characters	(Null)
93015 93035 93055 93075 93095 93115 93135 93155 93175 93195	TTL	Number: 300 to 65535	300

93215			
93235			
93255			
93275			
93295			
93315			
93335			
93355			
93016	Address	String:	(Null)
93036			
93056			
93076			
93096			
93116			
93136			
93156			
93176			
93196			
93216			
93236			
93256			
93276			
93296			
93316			
93336			
93356			

### SRV Settings

Pvalue	Description	Value range	Default
93008	Name	String:	(Null)
93028		Max length is 512	
93048		characters	
93068			
93088			
93108			
93128			
93148			
93168			
93188			
93208			

93228			
93248			
93268			
93288			
93308			
93328			
93348			
93009	TTL	Number:	300
93029		300 to 65535	
93049			
93069			
93089			
93109			
93129			
93149			
93169			
93189			
93209			
93229			
93249			
93269			
93289			
93309			
93329			
93349			
93010	Priority	Number:	0
93030		0 to 65535	
93050			
93070			
93090			
93110			
93130			
93150			
93170			
93190			
93210			
93230			
93250			
93270			
93290			
93310			

93330			
93350			
93011	Weight	Number: 0 to 65535	0
93031			
93051			
93071			
93091			
93111			
93131			
93151			
93171			
93191			
93211			
93231			
93251			
93271			
93291			
93311			
93331			
93351			
93012	Port	Number: 0 to 65535	0
93032			
93052			
93072			
93092			
93112			
93132			
93152			
93172			
93192			
93212			
93232			
93252			
93272			
93292			
93312			
93332			
93352			
93013	Target	String:	(Null)
93033			
93053			

93073			
93093			
93113			
93133			
93153			
93173			
93193			
93213			
93233			
93253			
93273			
93293			
93313			
93333			
93353			

### NAPTR Settings

Pvalue	Description	Value range	Default
93000	Name	String: Max length is 512 characters	(Null)
93020			
93040			
93060			
93080			
93100			
93120			
93140			
93160			
93180			
93200			
93220			
93240			
93260			
93280			
93300			
93320	TTL	Number: 300 to 65535	300
93340			
93001			
93021			
93041			
93061			



93081			
93101			
93121			
93141			
93161			
93181			
93201			
93221			
93241			
93261			
93281			
93301			
93321			
93341			
93002	Order	Number: 0 to 65535	0
93022			
93042			
93062			
93082			
93102			
93122			
93142			
93162			
93182			
93202			
93222			
93242			
93262			
93282			
93302			
93322			
93342			
93003	Preference	Number: 0 to 65535	0
93023			
93043			
93063			
93083			
93103			
93123			
93143			
93163			

93183			
93203			
93223			
93243			
93263			
93283			
93303			
93323			
93343			
93004	Flags	String:	(Null)
93024			
93044			
93064			
93084			
93104			
93124			
93144			
93164			
93184			
93204			
93224			
93244			
93264			
93284			
93304			
93324			
93344			
93005	Service	String: Max length is 512 characters	SIP+D2U
93025			
93045			
93065			
93085			
93105			
93125			
93145			
93165			
93185			
93205			
93225			
93245			
93265			

93285			
93305			
93325			
93345			
93006	Regexp	String:	(Null)
93026			
93046			
93066			
93086			
93106			
93126			
93146			
93166			
93186			
93206			
93226			
93246			
93266			
93286			
93306			
93326			
93346			
93007	Replacement	String:	(Null)
93027			
93047			
93067			
93087			
93107			
93127			
93147			
93167			
93187			
93207			
93227			
93247			
93267			
93287			
93307			
93327			
93347			

## Strict Password Rules

- **Web Configuration**

Users can find the configuration section in Web -> Maintenance->Web/SSH Access.

### Strict Password Rules

**Enable strict password rules**     No  Yes

**Minimum password length**   

**Required character classes**   

**Allowed character classes**     ▼

### Access Control Lists

- **Functionality**

This feature allows users to enable or disable the strict password rules, set the minimum password length, set the required number of character classes, and select the allowed character classes.

Pvalue	Description	Value Range	Default
28788	Enable strict password rules	0 – No 1 – Yes	0 – No
28790	Minimum password length	Number: 4 - 30	8
28791	Required number of character classes	Number: 0 - 3	3
28792	Allowed Character classes	Number: 7 – Lower case, upper case, numbers, 3 – Lower case, upper case, 5 – Lower case, numbers 6 – Upper case, numbers 11 – Lower case, upper case, special characters 13 – Lower case, numbers, special characters 14 – Upper case, numbers, special characters 9 – Lower case, special	7

		characters 10 – Upper case, special characters 12 – Numbers, special characters 1 – Lower case 2 – Upper case 4 – Numbers 8 – Special characters 15 - Lower case, upper case, numbers, special characters	
--	--	--	--

### Secondary NTP server

User can find the configuration section in Web -> Maintenance-> Date and Time.

**NTP Server**

---

**Secondary NTP Server**

---

**NTP Update Interval**

- **Functionality**

This feature allows users to configure the Secondary NTP Server. It defines the URL or IP address of the NTP server. The gateway may obtain the date and time from the server.

Pvalue	Description	Value Range	Default
8333	Secondary NTP Server	String: Server address	(Null)

### Local Time

User can find the configuration section in Web -> Maintenance-> Date and Time.


**Self-Defined Time Zone**

**Allow DHCP Option 2 to override time zone**  No  Yes

**Local Time**

- **Functionality**

This feature allows users to set device time from the host PC time via the browser. After clicking the bottom “Sync PC”, the device will pop up a window that will notice it synchronizes the local time.




Pvalue	Description	Value Range	Default
	Local Time	Button	(Null)

### T.38 Max Bit Rate

- **Web Configuration**

User can find the configuration section in Web -> Profile-> Fax Settings.



- **Functionality**

This feature allows users to select the maximum T. 38 bit rate. Lowering the maximum fax bit rate may help improve the fax success rate. Only effective when the fax machine is a fax receiver.

Pvalue	Description	Value Range	Default
28913	T.38 Max Bit Rate	Number:	2 - 9600bps
28914		1 - 4800bps	
28915		2 - 9600bps	
28916		3 - 14400bps	

## FIRMWARE VERSION 1.0.25.2

### PRODUCT NAME

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### DATE

05/23/2024

### FIRMWARE FILE INFORMATION

- GXW4216 V2 firmware file name: gxw4216v2fw.bin  
MD5: cd93ffcd8047010f26502ac5cd80c1ec
- GXW4224 V2 firmware file name: gxw4224v2fw.bin  
MD5: 9d43e89edf4099cfd0a9d7ce8e50dcd8
- GXW4232 V2 firmware file name: gxw4232v2fw.bin  
MD5: 934109f2261cbe2518f71f1af9972044
- GXV4248 V2 firmware file name: gxw4248v2fw.bin  
MD5: 0dd2b4994c174df158aae106e4fd8de8

### ENHANCEMENT

- Add IVR support to check the device's individual certificate information.
- Add support of variable \$PN and \$MAC in Config Server Path.

### BUG FIX

- Fixed unit can't establish SRTP Session after re-invite.
- Fixed a bug that caused the GXW device not to request the config file until a reboot.
- Fixed device continues to send the same credentials after the server responds with a 403 Forbidden.
- Fixed web UI wording change request for DNS SRV failover.
- Fixed device could use weak ciphers/key exchange for SSH.

## FIRMWARE VERSION 1.0.25.1

### PRODUCT NAME

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### DATE

04/26/2024

### FIRMWARE FILE INFORMATION

- GXW4216 V2 firmware file name: gxw4216v2fw.bin  
MD5: b7b8efa6c9770cd1024649a8a4388e1a
- GXW4224 V2 firmware file name: gxw4224v2fw.bin  
MD5: 275311195954abf9d91221b67d96f393
- GXW4232 V2 firmware file name: gxw4232v2fw.bin  
MD5: bebc5b66fa18c10eac262037f3d11001
- GXV4248 V2 firmware file name: gxw4248v2fw.bin  
MD5: eae705ecc47ee06a2410931740feff74

### ENHANCEMENT

- Set the “Disable User Level Web Access” (P28158) to “Yes” by default.
- Set the “Disable Viewer Level Web Access” (P28159) to “Yes” by default.
- Force user to change the password upon first login using the default password to the Admin/User/Viewer Account.

### BUG FIX

- Fixed an issue in the “Prompt Dial Tone Code” feature.



## FIRMWARE VERSION 1.0.23.2

### PRODUCT NAME

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### DATE

04/16/2024

### FIRMWARE FILE INFORMATION

- GXW4216 V2 firmware file name: gwx4216v2fw.bin  
MD5: 76ec50493c456d4b723542bcb6182e4c
- GXW4224 V2 firmware file name: gwx4224v2fw.bin  
MD5: 9d3ff361ebc9d5ba9e59979ce8c739d8
- GXW4232 V2 firmware file name: gwx4232v2fw.bin  
MD5: d54fbfd375495be0a7291eb1563a2c96
- GXV4248 V2 firmware file name: gwx4248v2fw.bin  
MD5: 5b481ef418f0ee94ef667c5679191246

### ENHANCEMENT

- Added Support for “Keep Security Setting After Reset”. [Keep Security Setting After Reset]

### BUG FIX

- Fixed a bug that caused SRTP to decrypt RTP fail causing one-way audio after a 20+ minute call.
- Fixed an issue in no audio on 200ok/ack with UAS on outbound calls.
- Fixed a bug that caused the device cannot connect to the OpenVPN server.
- Fixed unit can't establish SRTP Session after re-invite.
- Fixed the users' report of heavy static noise in the FXS TX audio.
- Fixed the inaccurate encoding and decoding of DTMF durations with SIP Info.
- Fixed the remote party perceived echo issue.
- Fixed a bug that caused DDNS does not work.
- Fixed unit stops responding after a couple of hours.
- Fixed an echo issue on the answering machine.

### NEW FEATURES OVERVIEW

This section lists major new features and describes how to use them from the user's point of view.

### Keep Security Setting After Reset

User can find the configuration section in Web -> Maintenance-> Security Settings-> Security

Validate Server Certificates  No  Yes  
 Keep Security Setting After Reset  No  Yes  
 Disable Weak TLS Cipher Suites

- **Functionality**

This feature depends on the reset lock feature. If enabled, security-related settings and trusted CA-related settings will be kept during different kinds of resetting.

Pvalue	Description	Value Range	Default
28849	Keep Security Setting After Reset	Number: 0 - No 1 - Yes	0 - No

## FIRMWARE VERSION 1.0.21.2

### PRODUCT NAME

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### DATE

12/11/2023

### FIRMWARE FILE INFORMATION

- GXW4216 V2 firmware file name: gwx4216v2fw.bin  
MD5: e85341789a1b6e63a9ec14ec1e3ab699
- GXW4224 V2 firmware file name: gwx4224v2fw.bin  
MD5: 33bb149f0865b53d2df5f48f6c4c385f
- GXW4232 V2 firmware file name: gwx4232v2fw.bin  
MD5: a1b2fd836c3920cbe428684c9a9a8ce6
- GXV4248 V2 firmware file name: gwx4248v2fw.bin  
MD5: 24a04dcc6af08a0ae1e8acbf560f0ce0

### ENHANCEMENT

- Added a “Provision” button which lets user provision manually via WebUI (Maintenance->Upgrade and Provisioning).
- Changed the order of download config file requests to cfgMAC.xml, cfgMAC, cfgMODEL.xml, and cfg.xml.

### BUG FIX

- Fixed a bug that caused DDNS not to work.
- Fixed a bug that caused the unit to stop responding after a couple of hours.
- Fixed an Issue with the registration.
- Fixed inaccurate encoding and decoding of DTMF durations.
- Fixed inaccurate encoding and decoding of DTMF durations with SIP Info.
- Fixed an issue to lock/unlock extensions from analog phones using local feature code.

## FIRMWARE VERSION 1.0.19.1

### PRODUCT NAME

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### DATE

10/18/2023

### FIRMWARE FILE INFORMATION

- GXW4216 V2 firmware file name: gxw4216v2fw.bin  
MD5: df90c238f735b911e0f5ed6663b9463d
- GXW4224 V2 firmware file name: gxw4224v2fw.bin  
MD5: 2ff527d407393e2bee4bfe84bea248c9
- GXW4232 V2 firmware file name: gxw4232v2fw.bin  
MD5: b690d7e42bd2590d3951b367bd5b4a48
- GXV4248 V2 firmware file name: gxw4248v2fw.bin  
MD5: 6faa1612321d88bd8415b21fe8ad141c

### ENHANCEMENT

- Added new value "4 - Auto" in NAT Traversal(P52/730/630/614).
- Added support AVS DTMF Detector Parameter. [AVS DTMF Detector Parameters]
- Add the ability to force local ringback tone with 180 ringing SDP. [Use P-Early-Media Header]  
[Ringback Tone at No Early Media]
- Added support Radius auth protocol. [Radius Auth Protocol]
- Add ability to lock/unlock extension from analog phones using local feature code.  
[Radius Auth Protocol]

User can find the configuration section in Web -> Maintenance-> RADIUS.

ontrol NO YES

**Action upon RADIUS Auth Server Error**  Reject Access  Authenticate Locally

---

**RADIUS Auth Protocol** PAP ▼

**RADIUS Auth Server Address**

**RADIUS Auth Server Port**

- **Functionality**

This feature allows users to configure RADIUS authentication protocol.

Pvalue	Description	Value Range	Default
28803	RADIUS Auth Protocol	Number: 0 – PAP 1 – CHAP 2 – MsCHAPv1 3 – MsCHAPv2	0 – PAP

Port Lock Code] [Radius Auth Protocol

User can find the configuration section in Web -> Maintenance-> RADIUS.

ontrol NO YES

**Action upon RADIUS Auth Server Error**  Reject Access  Authenticate Locally

---

**RADIUS Auth Protocol** PAP ▼

**RADIUS Auth Server Address**

**RADIUS Auth Server Port**

- **Functionality**

This feature allows users to configure RADIUS authentication protocol.

Pvalue	Description	Value Range	Default
28803	RADIUS Auth Protocol	Number: 0 – PAP 1 – CHAP 2 – MsCHAPv1 3 – MsCHAPv2	0 – PAP

**Port Lock Code**

User can find the configuration section in Web -> Advanced Settings-> System Features.

Prompt Dial Tone Code

**Port Lock Code**

**Play Busy Tone When Account is unregistered**  No  Yes

• **Functionality**

This feature allows users to configure with star code to unlock port 1- 48 with the dial out code. The default is \*21. The user is required to press \*21 and the four-digit locking code twice to set the lock code. To make a call, the user requires to press \*21 and then the locking code and then the actual number to dial out. If there is no locking code, the user dials out the actual number to make a call.

Pvalue	Description	Value Range	Default
24848	Port Lock Code	String: Digital Min Length 0 character Max Length 2 characters	21

Lock/Unlock Extension Code]

**BUG FIX**

- Fixed NAT Traversal does not have the "Auto" option.
- Fixed device the ringing frequency is "C=100/100;" , unable to answer.
- Fixed device sends registration information all the time.
- Fixed device produces core dump file when config Internet Protocol to "Both, prefer IPv6".
- Fixed FXS18 off hook failed after long time performance.
- Fixed the Call Waiting CID cannot be displayed.
- Fixed an echo issue during the call.
- Fixed wrong time when using DHCP option 2 for Timezone.
- Fixed device does not process DTMF on early media stage.
- Fixed the admin/Viewer/user password containing 'spaces' can be saved but not effective.
- Fixed using G723 to make phone calls and generate core files.
- Fixed unable to show caller ID when the number begins with "#".
- Fixed device didn't play DTMF tone when auxiliary equipment only supports in audio.
- Fixed AVS misreporting DTMF information during FXS calls.
- Fixed the Inaccurate encoding and decoding of DTMF durations with SIP Info.
- Fixed the DTMF tones cause device to not send audio.
- Fixed the poor echo processing during a call.
- Fixed device sends a fax to the auxiliary, and the response to be tested is 500.
- Fixed when the device starts requesting files, the LCD keeps flashing after turning off the server, and the page cannot be restarted.
- Fixed inaccurate encoding and decoding of DTMF durations.

- Fixed Gateway does not use NTP server from DHCP option 42.
- Fixed provisioning will reset some parameters.

## NEW FEATURES OVERVIEW

This section lists major new features and describes how to use them from the user's point of view.

### AVS DTMF Detector Parameters

User can find the configuration section in Web -> Profile-> Audio Settings.

<b>DSP DTMF Detector Min Level</b>	<input type="text" value="-25"/>	dBm
<b>DSP DTMF Detector SNR</b>	<input type="text" value="1"/>	
<b>DSP DTMF Detector Deviation</b>	<input type="text" value="25"/>	%
<b>DSP DTMF Detector Twist</b>	<input type="text" value="5"/>	dB

- **Functionality**

This feature allows users to configure the AVS DTMF detector related parameters. DSP DTMF Detector Min Level sets the minimum level required for DTMF tone to be considered valid, DSP DTMF Detector SNR sets the Maximum signal-to-noise ratio required for DTMF tone to be considered valid, DSP DTMF Detector Deviation sets the deviation, above and below the central frequency, DSP DTMF Detector Twist sets the maximum value by which one frequency energy level can surpass another frequency energy level.

Pvalue	Description	Value Range	Default
28804 28805 28806 28807	DSP DTMF Detector Min Level	Number: -45 – 0	-25
28808 28809 28810 28811	DSP DTMF Detector SNR	Number: 0 – 2	1
28812 28813 28814 28815	DSP DTMF Detector Deviation	Number: 0 – 25	25
28816 28817 28818	DSP DTMF Detector Twist	Number: 0 – 12	5

28819			
-------	--	--	--

### Use P-Early-Media Header

User can find the configuration section in Web -> Profile-> SIP Settings-> Basic Settings.

**Use P-Emergency-Info Header**     No  Yes

**Use P-Asserted-Identity Header**     No  Yes

**Use P-Early-Media Header**     No  Yes

**SIP REGISTER Contact Header Uses**     LAN Address  WAN Address

- Functionality**

This feature allows users to configure the Use P-Early-Media Header. It controls whether the P-Early-Media Header support is enabled.

Pvalue	Description	Value Range	Default
60072	Use P-Early-Media Header	Number:	0 – No
60172		0 – No	
60272		1 – Yes	
60372			

### Ringback Tone at No Early Media

User can find the configuration section in Web -> Profile-> Call Settings

**Callee Flash to 3WC**     No  Yes

**Ring Timeout**   

**Ringback Tone at No Early Media**     No  Yes

**Delayed Call Forward Wait Time**   

**Send Anonymous**     No  Yes

- Functionality**

This feature allows users to configure the Ringback Tone at No Early Media. If yes, play ringback tone when there is no receiving early media RTP packets.

Pvalue	Description	Value Range	Default
60073	Ringback Tone at No Early Media	Number:	0 – No
60173		0 – No	
60273		1 – Yes	



60373			
-------	--	--	--

### RADIUS Auth Protocol

User can find the configuration section in Web -> Maintenance-> RADIUS.

NO  YES  
**Action upon RADIUS Auth Server Error**  
 Reject Access  Authenticate Locally

**RADIUS Auth Protocol**

**RADIUS Auth Server Address**

**RADIUS Auth Server Port**

PAP  
 PAP  
 CHAP  
 MsCHAPv1  
 MsCHAPv2  
 1012

- Functionality**

This feature allows users to configure RADIUS authentication protocol.

Pvalue	Description	Value Range	Default
28803	RADIUS Auth Protocol	Number: 0 – PAP 1 – CHAP 2 – MsCHAPv1 3 – MsCHAPv2	0 – PAP

### Port Lock Code

User can find the configuration section in Web -> Advanced Settings-> System Features.

**Prompt Dial Tone Code**

**Port Lock Code** 21

**Play Busy Tone When Account is unregistered**  No  Yes

- Functionality**

This feature allows users to configure with star code to unlock port 1- 48 with the dial out code. The default is \*21. The user is required to press \*21 and the four-digit locking code twice to set the lock code. To make a call, the user requires to press \*21 and then the locking code and then the actual number to dial out. If there is no locking code, the user dials out the actual number to make a call.

Pvalue	Description	Value Range	Default
--------	-------------	-------------	---------

24848	Port Lock Code	String: Digital Min Length 0 character Max Length 2 characters	21
-------	----------------	--	----

### Lock/Unlock Extension Code

User can find the configuration section in Web -> FXS Ports-> Advanced Port Settings.

## Advanced Port Settings

Port	Offhook Auto-dial	Hunting Group	Request URI Routing ID	Lock/Unlock extension code
FXS 1	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 2	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 3	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 4	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 5	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 6	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 7	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 8	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 9	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 10	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 11	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 12	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 13	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 14	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 15	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>
FXS 16	<input type="text"/>	None ▾	<input type="text"/>	<input type="text"/>

- Functionality**

This feature allows users to configure the locking extension for ports 1 to 48.

Pvalue	Description	Value Range	Default
24800 ~ 24847	Lock/Unlock extension code	String: Digital Min Length 4 characters Max Length 4 characters	(Null)

## **FIRMWARE VERSION 1.0.17.1**

### **PRODUCT NAME**

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### **DATE**

09/05/2023

### **FIRMWARE FILE INFORMATION**

- GXW4216 V2 firmware file name: gwx4216v2fw.bin  
MD5: 9c6ab45d776052c0a746d621c4b4358a
- GXW4224 V2 firmware file name: gwx4224v2fw.bin  
MD5: c172564346c5c13d445a93499f58f66c
- GXW4232 V2 firmware file name: gwx4232v2fw.bin

MD5: d947f0f6a95d8eb15b757cb175ff05af

- GXV4248 V2 firmware file name: gxw4248v2fw.bin

MD5: 5bcf5304c510c0ffa10f530d0df34ef6

## ENHANCEMENT

- Updated the “Replace Beginning '+' in Caller ID with” support a predefined string. (Pvalue changed from P29073/29173/29273/29373 to P60083/60183/60283/60383). [Replace the beginning '+' in Caller ID with]
- Added the new option “3 - PR” in “Visual MWI type(P4371/4372/4373/4374)” which sends MWI signaling using Polarity Reversal.
- Added support the “ = ” sign in config and firmware server path.
- Updated “Prefer Primary SIP Server(P4567/4568/4569/4570)” options “1 – Yes” to “1 - Will register to primary server if failover server registration expires, and 2 - Will register to primary server if primary server responds”.

## BUG FIX

- Fixed device didn't support TLS1.
- Fixed device unable to import mib file to PRTG.
- Fixed the inaccurate encoding and decoding of DTMF durations with SIP Info.
- Fixed device unit sends cancel to sip server during IP call.
- Fixed MWI with NEON does not work when using ETSI-DTMF.
- Fixed SIP Server cannot contain hyphens.
- Fixed gateway fails to authenticate web access using the Radius server.
- Fixed system prompt "incorrect password" despite keying the correct PIN code for outbound calls.
- Fixed login to the web using GXW4248V2, some functions in French and Spanish are not translated.

## NEW FEATURES OVERVIEW

This section lists major new features and describes how to use them from the user's point of view.

### Replace the beginning '+' in Caller ID with

User can find the configuration section in Web -> Profile-> Call Settings.

**Anonymous Call Rejection**  No  Yes

**Replace Beginning '+' in Caller ID with**

**Hunting Group Type**  Circular  Linear

- **Functionality**

This feature allows users to configure the Replace the beginning '+' in Caller ID with the configured string when sending the Caller ID to the analog phone.

Pvalue	Description	Value Range	Default
60083	Replace the beginning '+' in Caller ID with	String: number 0 - 9 Max length is 6 characters.	(Null)
60183			
60283			
60383			

## FIRMWARE VERSION 1.0.15.2

### PRODUCT NAME

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### DATE

05/05/2023

### FIRMWARE FILE INFORMATION

- GXW4216 V2 firmware file name: gxw4216v2fw.bin  
MD5: 09c9f1e50fb415992255021bdc3cf500
- GXW4224 V2 firmware file name: gxw4224v2fw.bin  
MD5: f14a8effc22f22d1318d0d64c2b01ff6
- GXW4232 V2 firmware file name: gxw4232v2fw.bin  
MD5: b70779dd73ea79c333f65df8c52dc8b2
- GXV4248 V2 firmware file name: gxw4248v2fw.bin  
MD5: b2aee974a3ccc9010b734cae1da37ebb

## ENHANCEMENT

- Add the Ability to specify DTMF timing for InBand [Custom DTMF InBand Duration]

## BUG FIX

- Fixed the device using a random sip port requires a reboot to take effect.
- Fixed No Audio on incoming transferred calls in external calls.
- Fixed device unit sends BYE with the wrong CSeq.
- Fixed Special Proceed Indication Tone is overridden by Special Condition Tone with GIBTELECOM ITSP.
- Fixed after closing SIP registration, re-open SIP registration, and the device sends two registration requests.
- Fixed device uploads too large error format configuration file without a prompt on the web.
- Fixed the Authenticate server certificate domain/chain option actually needs to be restarted to take effect.
- Fixed the wrong time when using DHCP option 2 for the time zone.

## NEW FEATURES OVERVIEW

This section lists major new features and describes how to use them from the user's point of view.

### Custom DTMF InBand Duration

User can find the configuration section in Web -> Profile-> Audio Settings.

**DTMF Payload Type**

---

**Custom DTMF InBand Duration** Duration:  ms, Inter Duration:  ms

- **Functionality**

This feature allows users to configure the Custom DTMF InBand Duration. If "Duration" is 0, the gateway will totally pass-through transfer the InBand DTMF from the analog agent side; If "Duration" is not 0, we can use this feature to customize the duration and inter-duration of InBand DTMF; The valid range of "Duration" is 0 or 40~2000ms, the valid range of "Inter-Duration" is 40~2000ms.

Pvalue	Description	Value Range	Default
28134	Custom DTMF InBand Duration: Duration	Number:	0
28135		0 or 40~2000 (ms)	
28136			
28137			
28138	Custom DTMF InBand Duration: Inter Duration	Number:	50
28139		0 or 40~2000 (ms)	
28140			
28141			

## FIRMWARE VERSION 1.0.13.2

### PRODUCT NAME

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### DATE

03/10/2023

### FIRMWARE FILE INFORMATION

- GXW4216 V2 firmware file name: gxw4216v2fw.bin  
MD5: 9dc017b2c45f10851c620e4a831722ea
- GXW4224 V2 firmware file name: gxw4224v2fw.bin  
MD5: eca6b6bdab56e9eb8a6dae86c0265d58
- GXW4232 V2 firmware file name: gxw4232v2fw.bin  
MD5: e48304a7dc3a998fd1e8fd0de81a9a2e
- GXV4248 V2 firmware file name: gxw4248v2fw.bin  
MD5: b8525f3f7b6a0d8a586c8de32f96b1b2

## ENHANCEMENT

- Added support for the MWI Tone. [MWI Tone]
- Added support for the Special Proceed Indication Tone. [Special Proceed Indication Tone].
- Added support for the Special Condition Tone. [Special Condition Tone]
- Add the ability to ignore the alert-info header. [Ignore Alert-Info Header]
- Added support for “Extra Debug” in Syslog Level.
- Update the status page to show the HW version with the model’s name.
- Added the ability to configure special features with GIBTELECOM via TR069.

## BUG FIX

- Fixed the device cannot log in to the web if the password length exceeds 18 characters.
- Fixed after closing SIP registration, re-open SIP registration, and the device sends two registration requests.
- Fixed the Inbound long-duration call fails under certain configurations.
- Fixed Config Server Path does not support the "+" character.
- Fixed an off-hook delay problem that occurs when the FAX runs for a long period.
- Fixed device the off hook not detected during ringing.
- Fixed device with no dial tone when pressing Flash+4 to make a transfer.
- Fixed when the failover SIP server address is domain name plus port registration, and the sending destination port is wrong.
- Fixed device unit does not allow/send DTMF A B C D digits.
- Fixed an issue that no audio for the second call received.
- Fixed a bug in which Syslog is enabled on the HT device in the local deployment, and the content of the syslog package is empty.
- Fixed the authenticate server certificate domain/chain option needs to be restarted to take effect.
- Fixed an issue that causes DTMF data sent in disorder.
- Fixed Registration with a random port after a reboot.
- Fixed the product model display error on the status page in other languages except in English.

## NEW FEATURES OVERVIEW

This section lists major new features and describes how to use them from the user’s point of view.

### MWI Tone

User can find the configuration section in Web -> Profile-> Call Settings.

**Visual MWI Type**     FSK    NEON

**MWI Tone**     Default    Special Proceed Indication Tone

**Transfer on Conference Hangup**     No    Yes

- **Functionality**



This feature allows users to configure the MWI tone for the voice mail, the device will play the MWI tone when the user picks up. The default is the Stuttgart dial tone.

Pvalue	Description	Value Range	Default
28197	MWI Tone	0 – Default	0 – Default
28198		1 – Special Proceed	
28199		Indication Tone	
28200			

### Special Proceed Indication Tone

- Web Configuration**

User can find the configuration section in Web -> Advanced Settings-> Ring Tones.

<b>Conference Party Hangup Tone</b>	<input type="text" value="f1=425@-15,c=600/600;"/>
<b>Special Proceed Indication Tone</b>	<input type="text" value="f1=350@-13, f2=440@-13, c=750/750-0/0;"/>
<b>Special Condition Tone</b>	<input type="text" value="f1=350@-13, f2=450@-13, c=750/750;"/>

- Functionality**

This feature allows users to configure the special process indicator tone for the voice mail, the device will play the MWI tone when the user picks up. The default is the Stuttgart dial tone.

Pvalue	Description	Value Range	Default
28196	Special Proceed Indication Tone	String Max Length: 256	f1=350@-13, f2=440@-13, c=750/750-0/0;

### Special Condition Tone

- Web Configuration**

User can find the configuration section in Web -> Advanced Settings-> Ring Tones.

<b>Special Proceed Indication Tone</b>	<input type="text" value="f1=350@-13, f2=440@-13, c=750/750-0/0;"/>
<b>Special Condition Tone</b>	<input type="text" value="f1=350@-13, f2=450@-13, c=750/750;"/>

- Functionality**

This feature allows users to configure the special condition tone. When a user is activated using the GIBTELECOM in Special Feature. the SIP server sends a NOTIFY with "special-condition-tone". The

"Special Condition Tone" will be played instead of the "Dial Tone".

Pvalue	Description	Value Range	Default
28211	Special Proceed Indication Tone	String Max Length: 256	f1=350@-13, f2=450@-13, c=750/750;

### Ignore Alert-Info Header

User can find the configuration section in Web -> Profile-> SIP Settings-> Basic Settings

**CONTACT WITH TCP/TLS**

**Allow SIP Factory Reset**     No    Yes

**Ignore Alert-Info Header**     No    Yes

**SIP User-Agent**

- **Functionality**

This feature allows users to configure Ignore Alert-Info Header. It is configured to play the default ringtone by ignoring the Alert-Info header.

Pvalue	Description	Value Range	Default
26018	Ignore Alert-Info Header	0 – No	0 – No
26118		1 – Yes	
26218			
26318			



## FIRMWARE VERSION 1.0.11.2

### PRODUCT NAME

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### DATE

01/10/2023

### FIRMWARE FILE INFORMATION

- GXW4216 V2 firmware file name: gxw4216v2fw.bin  
MD5: 25b13af159971fa80864cb2a810fa8e5
- GXW4224 V2 firmware file name: gxw4224v2fw.bin  
MD5: 031ff3bde2f9b475a8a0440bb8f01c50
- GXW4232 V2 firmware file name: gxw4232v2fw.bin  
MD5: 937387890687f4bf8d1711caef73a0d7
- GXV4248 V2 firmware file name: gxw4248v2fw.bin  
MD5: 55a63fbf82b950774e1da645e53ecea

### ENHANCEMENT

- Added support for Download and Process All Available Config Files. [Download and Process All Available Config Files].
- Added the new voice prompt \*98.
- Added the additional Flash digit events in the Special Feature Gibtelecom.
- Added support for new override config file option in “cfgMAC\_override.xml”.
- Added Pvalue not on WebUI:  
P8615 - Disable filename in URL for config provision. (1 -Yes, 0 – No. Default is 0)  
P8616 - Disable filename in URL for firmware upgrade. (1 -Yes, 0 – No. Default is 0)

### BUG FIX

- Fixed the device responds with not found while configured with a non-profile1 account
- Fixed an issue that made account status under profile4 displayed incorrectly.
- Fixed device will display Registered abnormal after changing the profile ID via GDMS.
- Fixed the sip server address and port settings that do not conform to the rules can be saved.
- Fixed the Call waiting dropped by MTAS Server.

- Fixed Local RBT is not played after 180 ringing.
- Fixed the call that cannot be held the current one is valid\_close SRTP\_\*19.
- Fixed the WebUI description error due to the Increase Password length for GXW42xx V2
- Fixed an issue that caused the FXS port test failure.
- Fixed the software stops when using the "Replace Beginning '+' with 00 in Caller ID" feature.
- Fixed DTMF Negotiation Fails Upon Transfer.
- Fixed the device cannot be started and core files are generated after several months of standby.
- Fixed Call quality data not reported after the factory reset.
- Fixed Modifying sip accounts on the web page does not report user modification.
- Fixed a bug that the device only read the first ten FXS ports' DND status.

## NEW FEATURES OVERVIEW

This section lists major new features and describes how to use it from the user's point of view.

### Download and Process All Available Config Files

- **Web Configuration**

User can find the configuration section in Web -> Maintenance-> Upgrade and Provisioning.

Config File Postfix

Enable using tags in URL  No  Yes

**Download and Process All Available Config Files**  No  Yes

Allow DHCP Option 43 and Option 66 to Override Server  No  Yes

- **Functionality**

This feature allows users to inverse download all config files. If set to Yes, the device will download and apply (overwrite) all available configs in the order of cfg.xml, cfgProductModel.xml, cfgMAC.xml, cfgMAC, cfgMAC\_override.xml, and "DHCP option 67 bootfile".

Pvalue	Description	Value range	Default
8467	Download and Process ALL Available Config Files	0 – No 1 - Yes	0 – No

## FIRMWARE VERSION 1.0.9.1

### PRODUCT NAME

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### DATE

11/04/2022

### FIRMWARE FILE INFORMATION

- GXW4216 V2 firmware file name: gxw4216v2fw.bin  
MD5: aa17d02a9ec1057f87dad431e6236dfc
- GXW4224 V2 firmware file name: gxw4224v2fw.bin  
MD5: 497ce530a95abb5af9bcfdc96e0ca351
- GXW4232 V2 firmware file name: gxw4232v2fw.bin  
MD5: 9eb3321e7c99f1d7c138a22e771b59e2
- GXV4248 V2 firmware file name: gxw4248v2fw.bin  
MD5: ca2c2645283a067299043b92fb7f8bf6

### ENHANCEMENT

- Increased the Admin, User, and Viewer Password length to 30.

### BUG FIX

- Fixed devices send wrong call status reports as P2P after the local three-party conference ends.
- Fixed sips TLS registration failed after filling in the Custom Certificate with the GEN 1 certificate.
- Fixed a bug that caused units to lose registration randomly.
- Fixed a ringing multiple ports behavior issue.
- Fixed devices Cannot enable the local call feature using a certain dial plan.
- Fixed the forced SRTP (\*18) function is not effective when it is currently effective.
- Fixed a ringing multiple ports behavior issue.
- Fixed an issue that causes the content of the sip log file to be incomplete.
- Fixed the ACS URL does not clear up empty after reset.

## FIRMWARE VERSION 1.0.7.2

### PRODUCT NAME

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### DATE

10/11/2022

### FIRMWARE FILE INFORMATION

- GXW4216 V2 firmware file name: gxw4216v2fw.bin  
MD5: 8fbf066a6e0a4a6beb7b3742eab21830
- GXW4224 V2 firmware file name: gxw4224v2fw.bin  
MD5: f603948cc2161bc139551edda284b583
- GXW4232 V2 firmware file name: gxw4232v2fw.bin  
MD5: c53c9c3e17aed2c4fe982191c6028a0d
- GXV4248 V2 firmware file name: gxw4248v2fw.bin  
MD5: bb97654874cb33598671a93f27ec9dcb

### ENHANCEMENT

- Added support to Define the Preferred Provisioning Method. [Configuration File Types Allowed]
- Added support of DHCP Option 150. [Additional Override DHCP Option]
- Added support for SRTP Key Length. [SRTP Key Length]
- Added support for SSL Key Log File. [With Secret Key Information]
- Added support for Security Controls for SSH Access. [Security Controls for SSH Access]
- Added support for Enable using tags in URL. [Enable using tags in URL]
- Updated Syslog to make user reading more friendly.

### BUG FIX

- Fixed the device's no audio and randomly reboot issues after the upgrade.
- Fixed a ringing multiple ports behavior issue.
- Fixed devices Cannot enable the local call feature using a certain dial plan.
- Fixed a device upgrade failed issue due to out of memory.
- Fixed a fax transmission issue between GXW42xx devices.
- Fixed device ACS URL not set to "https://acs.gdms.cloud" by default.
- Fixed a bug that caused the call is abnormal after the participant transfers the call.

- Fixed device some vulnerabilities appear while scanning.
- Fixed device the status light is abnormal after the FTP upgrade fails.
- Fixed a wrong error prompt in uploading the configuration file.
- Fixed a bug that causes the device will turn off the LCD screen Led after 5 minutes.
- Fixed Uptime on French mode display abnormal on Web UI.
- Fixed a bug that causes fax T.38 always to fail with SPA112.
- Fixed device always sends DTMF event # after using # as the dial key.
- Fixed the MAC on the device info page is not fully displayed.
- Fixed VLAN name and management address identification are missing in the reporting information at startup.

## NEW FEATURES OVERVIEW

This section lists major new features and describes how to use them from the user's point of view.

### Configuration File Types Allowed

- **Web Configuration**

User can find the configuration in Web UI -> Maintenance-> Upgrade and Provisioning.

**Authenticate Conf File**     No  Yes

**Firmware Key**   

**Configuration File Types Allowed**     ▼

- **Functionality**

This feature allows users to choose Allowed Configuration File Types, All or XML Only.

- **New P Values**

Pvalue	Description	Value range	Default
P8601	Configuration File Types Allowed	47 – All 46 – XML Only	47 – All

### Additional Override DHCP Option

- **Web Configuration**

User can find the configuration in Web UI -> Maintenance-> Upgrade and Provisioning.



**Allow DHCP Option 43 and Option 66 to Override Server**  No  Yes

**Additional Override DHCP Option**

**3CX Auto Provision**  No  Yes

- Functionality**

This feature allows users to configure additional DHCP Option to be used for the firmware server instead of the configured firmware server or the server from DHCP Option 43 and 66.

- New P Values**

Pvalue	Description	Value range	Default
P8337	Additional Override DHCP Option	0 – None 1 – Option 150	0 – None

### SRTP Key Length

User can find the configuration in Web UI -> Profile-> Audio Settings.

**SRTP Mode**

**SRTP Key Length**

**Crypto Life Time**  No  Yes

- Functionality**

This feature allows users to configure the cipher method or key length if SRTP is enabled.

- New P Values**

Pvalue	Description	Value range	Default
P2383 P2483 P2583 P2683	SRTP Key Length	0 – AES 128&256 bit 1 – AES 128 bit 2 – AES 256 bit	0 - AES 128&256 bit

### With Secret Key Information

- Web Configuration**

User can find the configuration in Web UI -> Maintenance-> Ethernet Capture.

**With Secret Key Information**     No     Yes

**Status**    STOPPED

- **Functionality**

This feature allows users to configure whether the packet capture file contains secret key information or not.

- **New P Values**

Pvalue	Description	Value range	Default
P22419	With Secret Key Information	0 – No 1 – Yes	1 – Yes

### Security Controls for SSH Access

- **Web Configuration**

User can find the configuration in Web UI -> Maintenance-> Web/SSH Access.

**SSH Port**   

**Security Controls for SSH Access**

**Web Session Timeout**   

- **Functionality**

This feature allows users to configure security privileges.

- **New P Values**

Pvalue	Description	Value range	Default
P28210	Security Controls for SSH Access	0 – Only allow SSH private IP users to set system Pvalue 1 – Allow all SSH users to set system Pvalue 2 – Allow all SSH users to set any Pvalue 4 – Prohibit setting Pvalue	2 – Allow all SSH users to set any Pvalue

### Enable using tags in URL

- **Web Configuration**

User can find the configuration section in Web -> Maintenance-> Upgrade and Provisioning.

**Config File Postfix**

**Enable using tags in URL**     No    Yes

**Allow DHCP Option 43 and Option 66 to Override Server**     No    Yes

- **Functionality**

This feature allows users to enable using tags in Config Server Path.

- **New P Values**

Pvalue	Description	Value range	Default
P8609	Enable using tags in URL	0 – No 1 – Yes	1 – Yes

## FIRMWARE VERSION 1.0.5.4

### PRODUCT NAME

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### DATE

08/10/2022

### FIRMWARE FILE INFORMATION

- GXW4216 V2 firmware file name: gwx4216v2fw.bin  
MD5: a29a51c155d4a022532317a90b4257d8
- GXW4224 V2 firmware file name: gwx4224v2fw.bin  
MD5: c45cb6dd01f988a3ee6764dc2cf933c8
- GXW4232 V2 firmware file name: gwx4232v2fw.bin  
MD5: 0367ae67830df2929af5a275ca073b68
- GXV4248 V2 firmware file name: gwx4248v2fw.bin  
MD5: 96ae11e4682caacb20bd5ff59a8aa252

### ENHANCEMENT

- Added support to send SNMP traffic through Management Interface. [Enable SNMP Through Management Interface]
- Added support to send Syslog traffic through Management Interface. [Enable Syslog Through Management Interface]

### BUG FIX

- Fixed a bug that causes the core file to be generated after the device is turned on.
- Fixed download function of the page is display incorrect when accessing in User/Viewer account.
- Fixed device the log server domain name resolution order is incorrect.
- Fixed the copyright not translated into Russian on the Русский page.
- Fixed device will not send provision required when path contains the % character.
- Fixed the bug that causes IVR code reading is failed.
- Fixed an issue causes sometimes only one-way audio or no audio on both sides in the call.
- Fixed an issue that causes device faxes may not be sent and received normally.
- Fixed a WebUI error that causes the "Viewer Logout" button displayed as "XXXXX" in Chinese/Spanish/French language.

- Fixed an issue that causes the ATA device crash after it calls to itself.
- Fixed Dublin and Ireland are displayed incorrectly in Chinese in Time Zone.
- Fixed a bug that causes Call Waiting Tone syntax error.
- Fixed the incorrect description of 802.1X Mode.
- Fixed device the Syslog list will not be displayed when the system log level is EXTRA DEBUG.
- Fixed device cannot access the page and establish a call after unplugging and plugging the network cable on PPPoE and OpenVPN network.
- Fixed the web page lock time after the login error exceeds the limit will be timed again after clicking login again.


## NEW FEATURES OVERVIEW

This section lists major new features and describes how to use them from the user's point of view.

### Enable SNMP Through Management Interface

- **Web Configuration**

User can find the configuration in Web UI -> Maintenance-> Network Settings.



The screenshot shows a configuration page with a tab labeled 'Management access' and a dropdown menu set to 'Management interface only'. Below this, there are two radio button options: 'Enable SNMP Through Management Interface' (which is highlighted with a red box) and 'Enable Syslog Through Management Interface'. Both options have 'Enabled' and 'Disabled' radio buttons, with 'Disabled' being selected for both.

- **Functionality**

This feature allows users to choose whether to route the Syslog packets through management interface.

- **New P Values**

Pvalue	Description	Value range	Default
P28209	Enable SNMP Through Management Interface	1 – Enabled 0 – Disabled	0 – Disabled

### Enable Syslog Through Management Interface

- **Web Configuration**

User can find the configuration in Web UI -> Maintenance-> Network Settings.

**Enable SNMP Through Management Interface**     Enabled  Disabled

**Enable Syslog Through Management Interface**     Enabled  Disabled

**IP Address Mode for Management Interface**     DHCP  Static IP

- **Functionality**

This feature allows users to choose whether to route the Syslog packets through management interface

- **New P Values**

Pvalue	Description	Value range	Default
P8610	Enable Syslog Through Management Interface	1 – Enabled 0 – Disabled	0 – Disabled

## FIRMWARE VERSION 1.0.3.9

### PRODUCT NAME

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### DATE

08/08/2022

### FIRMWARE FILE INFORMATION

- GXW4216 V2 firmware file name: gxw4216v2fw.bin  
MD5: a29a51c155d4a022532317a90b4257d8
- GXW4224 V2 firmware file name: gxw4224v2fw.bin  
MD5: c45cb6dd01f988a3ee6764dc2cf933c8
- GXW4232 V2 firmware file name: gxw4232v2fw.bin  
MD5: 0367ae67830df2929af5a275ca073b68
- GXV4248 V2 firmware file name: gxw4248v2fw.bin  
MD5: 96ae11e4682caacb20bd5ff59a8aa252

### BUG FIX

- Fixed a bug that causes the device will ring with DND enabled.
- Fixed GXW4224V2 plays Priority Alert Call Waiting Tone incorrectly.
- Fixed GXW4224V2 plays Alternate Number Call Waiting Tone incorrectly.
- Fixed device cannot enable local call feature using a certain dial plan.
- Fixed the Firmware Server Path and the Config Server Path cannot save in "port/filename" format.
- Fixed the device does not prompt invalid input while entering illegal values in some parameters.
- Fixed a bug that caused the Syslog list information will not be cleared after hard key recovery.
- Fixed device off-hook LED status is wrong when LED Pattern config to A and existing voice mail.
- Fixed DTMF data sent in disorder.
- Fixed pressing flash +2 will hang up the other party's call after enabling flash digital control.
- Fixed a bug causes Second Register to have no auth header by default.
- Fixed REGISTER/INVITE failover retries are not the configured number.
- Fixed device does not prompt error "Max allow length 190" in local DNS.
- Fixed TIA-Inventory-Serial Number field is wrong in MAC address instead of Serial Number while captured in LLDP Wireshark trace file.

## FIRMWARE VERSION 1.0.3.4

### PRODUCT NAME

GXW4216 V2, GXW4224 V2, GXW4232 V2, GXW4248 V2

### DATE

05/13/2022

### FIRMWARE FILE INFORMATION

- GXW4216 V2 firmware file name: gwx4248v2fw.bin  
MD5: 6d628edd385a256f64df26beed929a1d
- GXW4224 V2 firmware file name: gwx4224v2fw.bin  
MD5 2b5ec23cdefd8d4ca1608a85b7b74f49
- GXW4232 V2 firmware file name: gwx4232v2fw.bin  
MD5: c4b23a63861bd09e9456be1c100d71d4
- GXV4248 V2 firmware file name: gwx4248v2fw.bin  
MD5: f92c28f2f7e918a7c6ffe684c7764779

### ENHANCEMENT

- This is the initial release version of GXW42xx V2 firmware