

GWN76xx Firmware Release Notes

IMPORTANT UPGRADING NOTE

- [9/26/2022] 1.0.23.14 for GWN7624 and GWN7625 has been released to fix the same SSH security bug in 9/19/2022 releases. Affected models are highly suggested to upgrade to the latest firmware.
- [9/19/2022] 1.0.23.6 for GWN7600/7600LR/7610/7660/7660LR/7664/7664LR and 1.0.23.13 for GWN7630/7630LR/7605/7605LR/7615 has been released. An SSH security bug has been fixed since this version. Affected models are highly suggested to upgrade to the latest firmware.
- [7/15/2021] [GWN7610 / GWN7600 / GWN7600LR] Please upgrade to 1.0.19.29 for security fix against Wi-Fi FragAttacks.
- [6/4/2021] [GWN7630 / GWN7630LR / GWN7605 / GWN7605LR / GWN7615] Please upgrade to 1.0.19.29 for security fix against Wi-Fi FragAttacks.
- [3/14/2020] [All APs 1.0.15.x] Due to the security enhancement, unless **Legacy TLS Compatibility** (only available on 1.0.15.4 or higher version) is enabled, master AP on 1.0.15.4 or higher firmware will not compatible with slave AP on firmware lower than 1.0.15.4. Master AP on firmware lower than 1.0.15.4 will also not be compatible with slave AP on firmware 1.0.15.4 or higher. Cloud and GWN Manager will still support both firmwares.
- [3/14/2020] [All APs 1.0.15.x] Do not use 1.0.15.x AP firmware with GWN7000 1.0.9.x or lower version.
- [12/14/2018] [All APs 1.0.8.17] In order to enable your AP's capability of connecting GWN Cloud EU server, AP needs to be upgraded to 1.0.8.17 or above.
- [6/15/2018] [GWN7600&7600LR 1.0.6.41] Starting from 1.0.6.x, GWN7600 and GWN7600LR will share same firmware file name gwn7600fw.bin. As a result, when GWN7600LR upgrades from pre-1.0.6.x to latest firmware, it will still retrieve firmware with name gwn7600lrfw.bin, and when GWN7600LR upgrades from 1.0.6.x or post-1.0.6.x to other firmware, it will retrieve firmware with name gwn7600fw.bin. So, when your GWN7600LR upgrades from pre-1.0.6.x firmware, you will need to manually modify the target firmware name to gwn7600lrfw.bin.
- [1/26/2017] [All APs 1.0.5.15] For firmware 1.0.5.15 (GWN7610) and 1.0.5.13 (GWN7600&GWN7600LR), this is only for GWN7610/GWN7600/GWN7600LR master deployment. All users

with GWN7000 as master are NOT encouraged to upgrade until 1.0.5.x matching firmware is available for GWN7000, due to the compatibility of new features.

- [8/11/2017] [All APs 1.0.4.22] Please upgrade to 1.0.4.12 or higher version to get the patch for WPA2 4-way handshake vulnerability.
- [8/11/2017] [GWN7610 1.0.3.21] Before starting to upgrade to latest firmware, please make sure your GWN7610's firmware version is 1.0.2.108 or higher. Also, please make sure your GWN7000 master (if any)'s firmware version is 1.0.2.71 or higher.

Table of Content

IMPORTANT UPGRADING NOTE	1
FIRMWARE FILE DOWNLOAD	7
[08/28/2025] FIRMWARE VERSION 1.0.25.13	8
PRODUCT NAME.....	8
DATE	8
FIRMWARE FILE INFORMATION	8
CHANGES/ENHANCEMENT	8
[08/27/2025] FIRMWARE VERSION 1.0.25.42	9
PRODUCT NAME.....	9
DATE	9
FIRMWARE FILE INFORMATION	9
CHANGES/ENHANCEMENT	9
[08/27/2025] FIRMWARE VERSION 1.0.25.41	10
PRODUCT NAME.....	10
DATE	10
FIRMWARE FILE INFORMATION	10
CHANGES/ENHANCEMENT	10
[08/15/2025] FIRMWARE VERSION 1.0.25.42	11
PRODUCT NAME.....	11
DATE	11
FIRMWARE FILE INFORMATION	11
CHANGES/ENHANCEMENT	11
[08/11/2025] FIRMWARE VERSION 1.0.25.10.....	12
PRODUCT NAME.....	12
DATE	12
FIRMWARE FILE INFORMATION	12
CHANGES/ENHANCEMENT	12
[05/09/2025] FIRMWARE VERSION 1.0.25.8	13
PRODUCT NAME.....	13
DATE	13
FIRMWARE FILE INFORMATION	13

CHANGES/ENHANCEMENT	13
[01/30/2025] FIRMWARE VERSION 1.0.25.8	14
PRODUCT NAME.....	14
DATE	14
FIRMWARE FILE INFORMATION	14
CHANGES/ENHANCEMENT	14
[01/28/2025] FIRMWARE VERSION 1.0.25.39	15
PRODUCT NAME.....	15
DATE	15
FIRMWARE FILE INFORMATION	15
CHANGES/ENHANCEMENT	15
[01/28/2025] FIRMWARE VERSION 1.0.25.38	16
PRODUCT NAME.....	16
DATE	16
FIRMWARE FILE INFORMATION	16
CHANGES/ENHANCEMENT	16
[10/1/2024] FIRMWARE VERSION 1.0.25.34	17
PRODUCT NAME.....	17
DATE	17
FIRMWARE FILE INFORMATION	17
CHANGES/ENHANCEMENT	17
[09/23/2024] FIRMWARE VERSION 1.0.25.34	18
PRODUCT NAME.....	18
DATE	18
FIRMWARE FILE INFORMATION	18
CHANGES/ENHANCEMENT	18
[6/26/2024] FIRMWARE VERSION 1.0.25.3	19
PRODUCT NAME.....	19
DATE	19
FIRMWARE FILE INFORMATION	19
CHANGES/ENHANCEMENT	19
[6/25/2024] FIRMWARE VERSION 1.0.25.2	20
PRODUCT NAME.....	20
DATE	20

FIRMWARE FILE INFORMATION	20
CHANGES/ENHANCEMENT	20
[06/07/2024] FIRMWARE VERSION 1.0.25.33	21
PRODUCT NAME.....	21
DATE	21
FIRMWARE FILE INFORMATION	21
CHANGES/ENHANCEMENT	21
NEW FEATURE OVERVIEW	22
[05/09/2024] FIRMWARE VERSION 1.0.25.19	23
PRODUCT NAME.....	23
DATE	23
FIRMWARE FILE INFORMATION	23
CHANGES/ENHANCEMENT	23
[04/05/2024] FIRMWARE VERSION 1.0.25.18	24
PRODUCT NAME.....	24
DATE	24
FIRMWARE FILE INFORMATION	24
CHANGES/ENHANCEMENT	24
NEW FEATURE OVERVIEW	24
[04/01/2024] FIRMWARE VERSION 1.0.25.2	26
PRODUCT NAME.....	26
DATE	26
FIRMWARE FILE INFORMATION	26
CHANGES/ENHANCEMENT	26
[02/07/2024] FIRMWARE VERSION 1.0.25.15	27
PRODUCT NAME.....	27
DATE	27
FIRMWARE FILE INFORMATION	27
CHANGES/ENHANCEMENT	27
[9/25/2023] FIRMWARE VERSION 1.0.25.10	28
PRODUCT NAME.....	28
DATE	28
FIRMWARE FILE INFORMATION	28
CHANGES/ENHANCEMENT	28
[8/21/2023] FIRMWARE VERSION 1.0.25.9	29

PRODUCT NAME.....	29
DATE	29
FIRMWARE FILE INFORMATION	29
CHANGES/ENHANCEMENT	29
[8/10/2023] FIRMWARE VERSION 1.0.25.8	30
PRODUCT NAME.....	30
DATE	30
FIRMWARE FILE INFORMATION	30
CHANGES/ENHANCEMENT	30
[7/24/2023] FIRMWARE VERSION 1.0.25.7	31
PRODUCT NAME.....	31
DATE	31
FIRMWARE FILE INFORMATION	31
CHANGES/ENHANCEMENT	31
NEW FEATURE OVERVIEW	32
[5/31/2023] FIRMWARE VERSION 1.0.25.3	34
PRODUCT NAME.....	34
DATE	34
FIRMWARE FILE INFORMATION	34
CHANGES/ENHANCEMENT	34
[5/19/2023] FIRMWARE VERSION 1.0.25.1	35
PRODUCT NAME.....	35
DATE	35
FIRMWARE FILE INFORMATION	35
CHANGES/ENHANCEMENT	35

FIRMWARE FILE DOWNLOAD

Individual firmware files are available for downloading at URL below:

<https://www.grandstream.com/support/firmware>

[08/28/2025] FIRMWARE VERSION 1.0.25.13

PRODUCT NAME

GWN7670 / GWN7670WM / GWN7672

DATE

08/28/2025

FIRMWARE FILE INFORMATION

- GWN7670/GWN7670WM Firmware file name: gwn7670fw.bin
MD5 checksum: bb8c74a955abb8fdec51368adf2fbb27
- GWN7672 Firmware file name: gwn7672fw.bin
MD5 checksum: e27ba27542efe50f85a95b4fcea6449a

CHANGES/ENHANCEMENT

- Internal bug fixes

[08/27/2025] FIRMWARE VERSION 1.0.25.42

PRODUCT NAME

GWN7664E / GWN7664ELR / GWN7665 / GWN7603 / GWN7605 / GWN7605LR

DATE

08/27/2025

FIRMWARE FILE INFORMATION

- GWN7664E/GWN7664ELR Firmware file name: gwn7664efw.bin
MD5 checksum: c98c73b4363d42dc6a4d721b669691b6
- GWN7665 Firmware file name: gwn7665fw.bin
MD5 checksum: bfce4c54ecd9230300900ca21d4ed837
- GWN7603 Firmware file name: gwn7603fw.bin
MD5 checksum: 9d51d53ab244b37db47b60a4ba5afd2d
- GWN7605/GWN7605LR Firmware file name: gwn7605fw.bin
MD5 checksum: 6a0d176593a0ab85e66eb67ac99d8058

CHANGES/ENHANCEMENT

- Fixed issue where IPv6 traffic was not occasionally tagged.
- Fixed performance degradation when VLANs are enabled.
- Fixed client disconnection issue due to 802.1X un-authentication failure.
- Fixed tagged traffic handling issue in access mode when DSCP is non-zero.
- Fixed long reconnection time issue after client reconnects to office Wi-Fi AP.
- Internal bug fixes

[08/27/2025] FIRMWARE VERSION 1.0.25.41

PRODUCT NAME

GWN7660 / GWN7660LR / GWN7661 / GWN7662 / GWN7664 / GWN7664LR / GWN7630 / GWN7630LR /
GWN7615 / GWN7624 / GWN7625

DATE

08/27/2025

FIRMWARE FILE INFORMATION

- GWN7660/GWN7660LR Firmware file name: gwn7660fw.bin
MD5 checksum: 785c3b759387247686f0f2e8a6d5b108
- GWN7661 Firmware file name: gwn7661fw.bin
MD5 checksum: a783039611d218066541d3960bbfcc87
- GWN7662 Firmware file name: gwn7662fw.bin
MD5 checksum: 2948a7e6ea8f461d91d39d298d8a8898
- GWN7664/GWN7664LR Firmware file name: gwn7664fw.bin
MD5 checksum: 026181144eaf02b5c06bb4a67aa7fd02
- GWN7630/GWN7630LR Firmware file name: gwn7630fw.bin
MD5 checksum: 624d1ddd79ea66da2744bf9622bbc15a
GWN7615 Firmware file name: gwn7615fw.bin
MD5 checksum: de5a2524f72e13add03a9f91f02a78a7
- GWN7624 Firmware file name: gwn7624fw.bin
MD5 checksum: 90d6f86aa983e3e15dfa80d44a133243
- GWN7625 Firmware file name: gwn7625fw.bin
MD5 checksum: c144e42c9c48f1737f68cf13db88db4b

CHANGES/ENHANCEMENT

- Fixed issue where IPv6 traffic was not occasionally tagged.
- Fixed device performance degradation when VLANs are enabled.
- Fixed client disconnection issue due to 802.1X un-authentication failure.
- Fixed tagged traffic handling issue in access mode when DSCP is non-zero.
- Fixed long reconnection time issue after client reconnects to office Wi-Fi AP.
- Internal bug fixes

[08/15/2025] FIRMWARE VERSION 1.0.25.42

PRODUCT NAME

GWN7660E / GWN7660ELR

DATE

08/15/2025

FIRMWARE FILE INFORMATION

- GWN7660E Firmware file name: gwn7660efw.bin
MD5 checksum: 3a62a55113566d7ffad820a3b9ae389d
- GWN7660ELR Firmware file name: gwn7660elrfw.bin
MD5 checksum: 91cc882fe11923f20a9ec7d79f9a1095

CHANGES/ENHANCEMENT

- Fixed issue where IPv6 traffic was not occasionally tagged.
- Fixed performance degradation when VLANs are enabled.
- Fixed client disconnection issue due to 802.1X un-authentication failure.
- Fixed tagged traffic handling issue in access mode when DSCP is non-zero.
- Fixed long reconnection time issue after client reconnects to office Wi-Fi AP.
- Internal bug fixes

[08/11/2025] FIRMWARE VERSION 1.0.25.10

PRODUCT NAME

GWN7604 / GWN7661E

DATE

08/11/2025

FIRMWARE FILE INFORMATION

- GWN7604 Firmware file name: gwn7604fw.bin
MD5 checksum: d3e19a0f0207b5754e94647dbd374795
- GWN7661E Firmware file name: gwn7661efw.bin
MD5 checksum: dc656a0f2c582179bfed1e71c04ed400

CHANGES/ENHANCEMENT

- Added DFS interface support for Thailand.
- Added Network Security Certification for EU RED 3.3.
- Fixed the tagged traffic handling issue with non-zero DSCP values.
- Fixed disconnect issue caused by abnormal multicast packets.
- Internal bug fixes

[05/09/2025] FIRMWARE VERSION 1.0.25.8

PRODUCT NAME

GWN7604 / GWN7661E

DATE

05/09/2025

FIRMWARE FILE INFORMATION

- GWN7604 Firmware file name: gwn7604fw.bin
MD5 checksum: d73b57107128cce73e85cf0cc175ad5d
- GWN7661E Firmware file name: gwn7661efw.bin
MD5 checksum: 4c0f808344fe57240f9d37d85a01ad44

CHANGES/ENHANCEMENT

- Fixed when management VLAN is set to value above 999, clients connected to SSID with Client IP Assignment=NAT unable to access internet issue.
- Fixed the issue on Captive Portal User Authentication with Microsoft Azure
- Allowed Norway channels
- Fixed RADIUS account and attribute issues.
- Fixed the phone rebooting after the pmksa expires issue.
- Internal bug fixes

[01/30/2025] FIRMWARE VERSION 1.0.25.8

PRODUCT NAME

GWN7670

DATE

01/30/2025

FIRMWARE FILE INFORMATION

- GWN7670 Firmware file name: gwn7670fw.bin
MD5 checksum: 3d1b8c0e017733d1033f2609f7e6f349

CHANGES/ENHANCEMENT

- This is the initial release for GWN7670

[01/28/2025] FIRMWARE VERSION 1.0.25.39

PRODUCT NAME

GWN7660E / GWN7660ELR / GWN7664E / GWN7664ELR

DATE

01/28/2025

FIRMWARE FILE INFORMATION

- GWN7660E Firmware file name: gwn7660efw.bin
MD5 checksum: f54af77bb1bb918cb2e91a505923b0e3
- GWN7660ELR Firmware file name: gwn7660elr fw.bin
MD5 checksum: fef77ec4e45c20fc096ccc7540f44ed4
- GWN7664E/GWN7664ELR Firmware file name: gwn7664efw.bin
MD5 checksum: 1f28913ce5960ffbb739134b004cb7d4

CHANGES/ENHANCEMENT

- Adapted the new Wi-Fi standards in some countries.
- Fixed Captive Portal user authentication issue with Microsoft Azure.
- Fixed SFP port not working when Ethernet port does not have link issue.
- Internal bug fixes

[01/28/2025] FIRMWARE VERSION 1.0.25.38

PRODUCT NAME

GWN7660 / GWN7660LR / GWN7661 / GWN7662 / GWN7664 / GWN7664LR / GWN7630 / GWN7630LR / GWN7605 / GWN7605LR / GWN7615

DATE

01/28/2025

FIRMWARE FILE INFORMATION

- GWN7660/GWN7660LR Firmware file name: gwn7660fw.bin
MD5 checksum: 6b8440c298c7e35449b1ce423190388b
- GWN7661 Firmware file name: gwn7661fw.bin
MD5 checksum: 70fc6987ed5a896ac70e6ed9b31110d8
- GWN7662 Firmware file name: gwn7662fw.bin
MD5 checksum: 5561a8cfd3f845c173fab18e3c1a6a59
- GWN7664/GWN7664LR Firmware file name: gwn7664fw.bin
MD5 checksum: ae86b324803bcab136aaa5503be89326
- GWN7630/GWN7630LR Firmware file name: gwn7630fw.bin
MD5 checksum: cc76fb0e7b6e65cc7127d88f99596b1d
- GWN7605/GWN7605LR Firmware file name: gwn7605fw.bin
MD5 checksum: 209da2bc2373dfbeff88062771a5fa36
- GWN7615 Firmware file name: gwn7615fw.bin
MD5 checksum: 026413b201000346c9602cc47cb80a05

CHANGES/ENHANCEMENT

- Adapted the new Wi-Fi standards in some countries.
- Fixed Norway DNF channels issue.
- Fixed some vulnerability issue.
- Fixed VLAN management related issue.
- Fixed Radius related issue.
- Internal bug fixes

[10/1/2024] FIRMWARE VERSION 1.0.25.34

PRODUCT NAME

GWN7660E / GWN7660ELR / GWN7664E / GWN7664ELR / GWN7665 / GWN7603

DATE

10/1/2024

FIRMWARE FILE INFORMATION

- GWN7660E Firmware file name: gwn7660efw.bin
MD5 checksum: 8f6f4be145d7a3f911f4a431764c42ec
- GWN7660ELR Firmware file name: gwn7660elrfw.bin
MD5 checksum: 2ef32a9a24d77b1dc63b6ce185266b76
- GWN7603 Firmware file name: gwn7603fw.bin
MD5 checksum: ff678ec7e0c3eb2235da45611eee501f
- GWN7664E/GWN7664ELR Firmware file name: gwn7664efw.bin
MD5 checksum: cfb6e080105f33d2fcb2f741e02c855c
- GWN7665 Firmware file name: gwn7665fw.bin
MD5 checksum: 499a035009843fa773a225737aca5fd8

CHANGES/ENHANCEMENT

- Fixed device randomly rebooting issue.
- Internal bug fixes

[09/23/2024] FIRMWARE VERSION 1.0.25.34

PRODUCT NAME

GWN7660 / GWN7660LR / GWN7661 / GWN7662 / GWN7664 / GWN7664LR / GWN7630 / GWN7630LR / GWN7605 / GWN7605LR / GWN7615 / GWN7624 / GWN7625

DATE

09/23/2024

FIRMWARE FILE INFORMATION

- GWN7660/GWN7660LR Firmware file name: gwn7660fw.bin
MD5 checksum: 79c246d8b908aae18bc76bbc54235c0f
- GWN7661 Firmware file name: gwn7661fw.bin
MD5 checksum: 7b32bcb3fae1c92b3c03bec61a233b6
- GWN7662 Firmware file name: gwn7662fw.bin
MD5 checksum: dabf47915eddc20e668f3b6665e9ed54
- GWN7664/GWN7664LR Firmware file name: gwn7664fw.bin
MD5 checksum: c968fcd501ea90974b89f178749318dd
- GWN7630/GWN7630LR Firmware file name: gwn7630fw.bin
MD5 checksum: b4d5dbd4daf994f45a83eae1c2838300
- GWN7605/GWN7605LR Firmware file name: gwn7605fw.bin
MD5 checksum: 806a07c8bda8e2a5b0ddcc9534c819d5
- GWN7615 Firmware file name: gwn7615fw.bin
MD5 checksum: 096a90c60a8dbfa02f24b35404a63ce8
- GWN7624 Firmware file name: gwn7624fw.bin
MD5 checksum: 3f4df75541c9b173a886d302459b4382
- GWN7625 Firmware file name: gwn7625fw.bin
MD5 checksum: f26c569069989dd70ce9aa70d0b90563

CHANGES/ENHANCEMENT

- Fixed device randomly rebooting issue.
- Fixed vulnerabilities issue.
- Internal bug fixes

[6/26/2024] FIRMWARE VERSION 1.0.25.3

PRODUCT NAME

GWN7660E

DATE

06/26/2024

FIRMWARE FILE INFORMATION

- GWN7660E Firmware file name: gwn7660efw.bin
MD5 checksum: 7fc170f6e0dbeb674bbf42d102e63882

CHANGES/ENHANCEMENT

- This is the initial release for GWN7660E

[6/25/2024] FIRMWARE VERSION 1.0.25.2

PRODUCT NAME

GWN7660ELR

DATE

06/25/2024

FIRMWARE FILE INFORMATION

- GWN7660ELR Firmware file name: gwn7660elrfw.bin
MD5 checksum: b802e925bc4c63455df593a96266e231

CHANGES/ENHANCEMENT

- This is the initial release for GWN7660ELR

[06/07/2024] FIRMWARE VERSION 1.0.25.33

PRODUCT NAME

GWN7600 / GWN7600LR / GWN7610 / GWN7660 / GWN7660LR / GWN7661 / GWN7662 / GWN7664 / GWN7664LR / GWN7630 / GWN7630LR / GWN7602 / GWN7605 / GWN7605LR / GWN7615 / GWN7624 / GWN7625

DATE

06/07/2024

FIRMWARE FILE INFORMATION

- GWN7600/GWN7600LR Firmware file name: gwn7600fw.bin
MD5 checksum: 2626d225865942a945aff5176e5980b7
- GWN7610 Firmware file name: gwn7610fw.bin
MD5 checksum: 31db915a45b524b3486dd6014fa7fb71
- GWN7660/GWN7660LR Firmware file name: gwn7660fw.bin
MD5 checksum: 3f69581b7807433a60025d49328af854
- GWN7661 Firmware file name: gwn7661fw.bin
MD5 checksum: b93ac12bc592ffb425d3ac34e702c4ea
- GWN7662 Firmware file name: gwn7662fw.bin
MD5 checksum: 29f43b8e1f545cbbab2e0d1d7b8a6f7e
- GWN7664/GWN7664LR Firmware file name: gwn7664fw.bin
MD5 checksum: 2350822ec4535af128e5cfc452888cb4
- GWN7630/GWN7630LR Firmware file name: gwn7630fw.bin
MD5 checksum: 0777f07e38e7ec288d583922441b7385
- GWN7602 Firmware file name: gwn7602fw.bin
MD5 checksum: abcf2f1b8d5e22bb0742a5e5bb7beb18
- GWN7605/GWN7605LR Firmware file name: gwn7605fw.bin
MD5 checksum: 827038fe04aeb7ca168fb5acecbfcd3a
- GWN7615 Firmware file name: gwn7615fw.bin
MD5 checksum: cddc73653f36a5e689bc7cc2fc2ce5e8
- GWN7624 Firmware file name: gwn7624fw.bin
MD5 checksum: a7e860137cdcd050208cc7622f2ad550
- GWN7625 Firmware file name: gwn7625fw.bin
MD5 checksum: 63bf31b6e1035e258a30a9e632dcca8f

CHANGES/ENHANCEMENT

- Added support for multi-VLAN Wi-Fi roaming.
- Added WP series device fast configuration support.

- Added support for MAC-Based RADIUS authentication (not supported on GWN7600/GWN7610/GWN7602)
- Added support of OS filtering
- Increased the number of MAC addresses which can be added in the Client isolation.
- Increased Whitelist/Blacklist limit to 1024. (not supported on GWN7600/GWN7610/GWN7602)
- Added **L2TPv3** tunnel support. (GWN7660/GWN7661/GWN7662/GWN7664)
- Added GWN anti-theft lock.
- Added LLDP protocol support.
- Added new **LED Pattern** for uplink down/no network.
- Fixed the unit does not broadcast SSID when added to the GWN Cloud/Manager issue.
- Fixed mesh connection delayed establishment issue.
- Fixed the unit randomly stops sending RADIUS authentication request issue.
- Fixed client randomly lost internet after connected to the AP issue.
- Fixed un-authorized clients can access internet via VPN issue.
- Fixed the devices display no usage when clients are connected and generating traffic issue.
- Fixed AP randomly reboot and generates core panic issue.
- Fixed clients unable to connect to AP unless rebooted issue.
- Fixed APs unable to pass RADIUS attribute 8 issue.
- Fixed devices use wrong MAC on the network issue.
- Internal bug fixes

NEW FEATURE OVERVIEW

- **New LED Pattern for uplink down/no network.**

This feature is supported on slave AP

- **Blue LED always on:** When slave AP successfully paired.
- **Flashing Purple LED:** When slave AP is disconnected due to no network, when GWN Cloud/Manager, or master device is disconnected.

[05/09/2024] FIRMWARE VERSION 1.0.25.19

PRODUCT NAME

GWN7600 / GWN7600LR / GWN7610 / GWN7660 / GWN7660LR / GWN7661 / GWN7662 / GWN7664 / GWN7664LR / GWN7630 / GWN7630LR / GWN7602 / GWN7605 / GWN7605LR / GWN7615 / GWN7624 / GWN7625

DATE

05/09/2024

FIRMWARE FILE INFORMATION

- GWN7600/GWN7600LR Firmware file name: gwn7600fw.bin
MD5 checksum: 443d43ab18ab65c4cbe1f9bb5b048356
- GWN7610 Firmware file name: gwn7610fw.bin
MD5 checksum: 18c8e351bb6d32e651083d20b45284da
- GWN7660/GWN7660LR Firmware file name: gwn7660fw.bin
MD5 checksum: 5e247d6f105f949c7e5bc04d58d74b91
- GWN7661 Firmware file name: gwn7661fw.bin
MD5 checksum: d0960c228a1a62a64f7c1eaa953135d1
- GWN7662 Firmware file name: gwn7662fw.bin
MD5 checksum: 00139e2044033e09b1a9e723401491dd
- GWN7664/GWN7664LR Firmware file name: gwn7664fw.bin
MD5 checksum: 93ab3a46617f35f81a1b88596efd1297
- GWN7630/GWN7630LR Firmware file name: gwn7630fw.bin
MD5 checksum: 3c13c9309732b545e3200115864bb197
- GWN7602 Firmware file name: gwn7602fw.bin
MD5 checksum: 70a0c864840a7a001616490e2816dbfd
- GWN7605/GWN7605LR Firmware file name: gwn7605fw.bin
MD5 checksum: 4b58d9f0d665b4c156849986dbf30b4d
- GWN7615 Firmware file name: gwn7615fw.bin
MD5 checksum: da2f47eb2c036a14c633c8646d10f9e1
- GWN7624 Firmware file name: gwn7624fw.bin
MD5 checksum: 804c70d5c75f3d4a873efe1d80735aa0
- GWN7625 Firmware file name: gwn7625fw.bin
MD5 checksum: 7c12926c792331ed018dfdb3185cc456

CHANGES/ENHANCEMENT

- Fixed the issue where non-admin accounts are disabled by default.
- Internal bug fixes

[04/05/2024] FIRMWARE VERSION 1.0.25.18

PRODUCT NAME

GWN7660/GWN7660LR

DATE

04/05/2024

FIRMWARE FILE INFORMATION

- GWN7660/GWN7660LR Firmware file name: gwn7660fw.bin
MD5 checksum: f23b95b7d462491390bdc773b841719e

CHANGES/ENHANCEMENT

- Added **L2TPv3** tunnel support
- Internal bug fixes

NEW FEATURE OVERVIEW

- **Added L2TPv3 tunnel support.**



This feature will allow admins to enable and configure L2TPv3 on the device. Please refer to the screenshots and options below.

Note: It is best to set the MTU to match the server to avoid network connectivity issues.

- **Name:** Set the name of the tunnel.
- **Encap Type:** Set the encapsulation type of the tunnel. Valid values for encapsulation are: UDP, IP.
- **Remote Server Address:** Set the IP address of the remote peer.
- **Local Tunnel ID:** Set the tunnel id, which is a 32-bit integer value. This uniquely identifies the tunnel.
- **Remote Tunnel ID:** Set the peer tunnel id, which is a 32-bit integer value assigned to the tunnel by the peer.
- **Local Session ID:** Set the session id, which is a 32-bit integer value. This uniquely identifies the session being created. The value used must match the peer_session_id value being used at the peer.
- **Remote Session ID:** Set the peer session id, which is a 32-bit integer value assigned to the session by the peer. The value used must match the session_id value being used at the peer.
- **Local Cookie:** Set an optional cookie value to be assigned to the session. This is a 4 or 8 byte value, specified as 8 or 16 hex digits, e.g. 014d3636deadbeef. The value must match the peer_cookie value set at the peer. The cookie value is carried in L2TP data packets and is checked for expected value at the peer. Default setting is no cookie used.
- **Remote Cookie:** Set an optional peer cookie value to be assigned to the session. This is a 4 or 8 byte value, specified as 8 or 16 hex digits, e.g. 014d3636deadbeef. The value must match the cookie value

set at the peer. It tells the local system what cookie value to expect to find in received L2TP packets. Default is no cookie used.

- **Tunnel VLAN ID:** The tunnel ID must be set in SSID, and make sure that SSID only has the AP(s) who enabled L2TPv3.



 The screenshot shows the 'Add' dialog box for configuring a new L2TPv3 service. The dialog has a title bar with 'Add' and a close button. Inside, there are several input fields: 'Name' (text), 'Enable' (checkbox), 'Encap Type' (dropdown menu with 'ip' selected), 'Remote Server Address' (text), 'Local TunnelID' (text), 'Remote Tunnel ID' (text with a help icon), 'Local Session ID' (text), 'Remote Session ID' (text with a help icon), 'MTU' (text with a help icon), 'Local Cookie' (text), 'Remote Cookie' (text with a help icon), and 'Tunnel VLAN ID' (text with a help icon). At the bottom of the dialog are 'Save' and 'Cancel' buttons.

[04/01/2024] FIRMWARE VERSION 1.0.25.2

PRODUCT NAME

GWN7603

DATE

04/01/2024

FIRMWARE FILE INFORMATION

- GWN7603 Firmware file name: gwn7603fw.bin
MD5 checksum: 6dbb60516b13575561f3b840ae84b5c0

CHANGES/ENHANCEMENT

- This is the initial release for GWN7603.

[02/07/2024] FIRMWARE VERSION 1.0.25.15

PRODUCT NAME

GWN7660 / GWN7660LR / GWN7661 / GWN7662 / GWN7664 / GWN7664LR

DATE

02/07/2024

FIRMWARE FILE INFORMATION

- GWN7660/GWN7660LR Firmware file name: gwn7660fw.bin
MD5 checksum: b9f7596cc0e58ecc1a6b4c30e85de6dd
- GWN7661 Firmware file name: gwn7661fw.bin
MD5 checksum: d15de4296c58fcc969f6e50d4994c73e
- GWN7662 Firmware file name: gwn7662fw.bin
MD5 checksum: b2695161b701306b379836018c4a7427
- GWN7664/GWN7664LR Firmware file name: gwn7664fw.bin
MD5 checksum: 2704e1d0c46cc8eeea57b45004949bbc

CHANGES/ENHANCEMENT

- Fixed devices display no usage issue.
- Fixed 2.4GHz randomly goes down issue.
- Fixed AP getting high memory usage alert and reboot issue.
- Fixed option 43 SSH representation incomplete issue.
- Fixed devices not able to connect to AP issue.
- Fixed device unable to pass Radius Attribute 8 issue.
- Internal bug fixes

[9/25/2023] FIRMWARE VERSION 1.0.25.10

PRODUCT NAME

GWN7600 / GWN7600LR / GWN7602 / GWN7605 / GWN7605LR / GWN7610 / GWN7615 / GWN7624 / GWN7625 / GWN7630 / GWN7630LR / GWN7660 / GWN7660LR / GWN7661 / GWN7662 / GWN7664 / GWN7664LR

DATE

09/25/2023

FIRMWARE FILE INFORMATION

- GWN7600/GWN7600LR Firmware file name: gwn7600fw.bin
MD5 checksum: 4f2c31ce8a61561836a26ba26a988688
- GWN7602 Firmware file name: gwn7602fw.bin
MD5 checksum: 557305b48670346b402272612149c62b
- GWN7605 Firmware file name: gwn7605fw.bin
MD5 checksum: 4618f0097fc8bc8f67d0e7f772ef26cf
- GWN7610 Firmware file name: gwn7610fw.bin
MD5 checksum: 46adad8e5dad13949448ebb4115adfa0
- GWN7615 Firmware file name: gwn7615fw.bin
MD5 checksum: 02b467a953ec10d1e7abf599548260b7
- GWN7624 Firmware file name: gwn7624fw.bin
MD5 checksum: b1504016daa8aed00851783874669ffa
- GWN7625 Firmware file name: gwn7625fw.bin
MD5 checksum: a57c870cb7dc335931e34aecdd3eb166b
- GWN7630/GWN7630LR Firmware file name: gwn7630fw.bin
MD5 checksum: 04851750a0166ee23c00d22164d927e0
- GWN7660/GWN7660LR Firmware file name: gwn7660fw.bin
MD5 checksum: d670a93746688c892ac26da1a0536362
- GWN7661 Firmware file name: gwn7661fw.bin
MD5 checksum: bdf04169774250d90bf3750d7c6115f7
- GWN7662 Firmware file name: gwn7662fw.bin
MD5 checksum: ccad3a8c586cfcdcdcee13d359ca56cc8
- GWN7664/GWN7664LR Firmware file name: gwn7664fw.bin
MD5 checksum: fa19b76ad61c4201b858e002a3f00adf

CHANGES/ENHANCEMENT

- Added support for Speed Test (**Not supported by GWN7610 & GWN7602**)
- Internal bug fixes

[8/21/2023] FIRMWARE VERSION 1.0.25.9

PRODUCT NAME

GWN7662

DATE

08/21/2023

FIRMWARE FILE INFORMATION

- GWN7662 Firmware file name: gwn7662fw.bin
MD5 checksum: 3bb8ef4c96ff8e9d0911b2aa7e678eb2

CHANGES/ENHANCEMENT

- Fixed device does not automatically fall back to 80M bandwidth when set to a fixed channel.

[8/10/2023] FIRMWARE VERSION 1.0.25.8

PRODUCT NAME

GWN7661

DATE

08/10/2023

FIRMWARE FILE INFORMATION

- GWN7661 Firmware file name: gwn7661fw.bin
MD5 checksum: fa6cf7fb95f4ce3c5414dfe30a311769

CHANGES/ENHANCEMENT

- Fixed device error and reboot after configuring multiple clients for syslog.
- Fixed the device restart abnormally after the band steering function is enabled.
- Fixed the AP cannot connect to internet when connected to the switch with the spanning tree enabled.

[7/24/2023] FIRMWARE VERSION 1.0.25.7

PRODUCT NAME

GWN7610 / GWN7600 / GWN7600LR / GWN7602 / GWN7615 / GWN7605 / GWN7605LR / GWN7630 / GWN7630LR / GWN7624 / GWN7625 / GWN7660 / GWN7660LR / GWN7664 / GWN7664LR

DATE

07/24/2023

FIRMWARE FILE INFORMATION

- GWN7610 Firmware file name: gwn7610fw.bin
MD5 checksum: 82f76dd2842d9feb99f3f7c96568bb31
- GWN7600/GWN7600LR Firmware file name: gwn7600fw.bin
MD5 checksum: 1b2c747359ef26d219bfbbb7c637e4f0
- GWN7602 Firmware file name: gwn7602fw.bin
MD5 checksum: 3f3730f21c2cfaa95869453843e3a7e
- GWN7615 Firmware file name: gwn7615fw.bin
MD5 checksum: f702e84289ea12c0179a3e0eabe79e0b
- GWN7605/GWN7605LR Firmware file name: gwn7605fw.bin
MD5 checksum: 149d7a9eed6307e1b840e280b8c3b501
- GWN7630/GWN7630LR Firmware file name: gwn7630fw.bin
MD5 checksum: 6047a2e2356fb4f51b718be5ca214ea9
- GWN7624 Firmware file name: gwn7624fw.bin
MD5 checksum: 6a03e981a15af54cec7b9dbad7027d91
- GWN7625 Firmware file name: gwn7625fw.bin
MD5 checksum: 001f2f5413bed501e39fa8451bd88aaa
- GWN7660/GWN7660LR Firmware file name: gwn7660fw.bin
MD5 checksum: 1d4d6f1459c809df7ec97b8eab0e9aa1
- GWN7664/GWN7664LR Firmware file name: gwn7664fw.bin
MD5 checksum: 555e6f514b72a35d057126a7bdebedd2

CHANGES/ENHANCEMENT

- Increased PPSK profiles.
- Increased the client expiration time to 30 days.
- Added device name in syslog messages.
- Added 80MHz channel width in Indonesia country for the 5G band.
- Added support for timestamp and security signature on the URL redirect.
- Fixed radio configuration about DFS channel does not take effect.
- Fixed slave AP automatically factory reset when transferring to the Manager.
- Fixed obscured characters from the schedule name.

- Modified the countermeasure prompt.
- Fixed terminal VLAN ID and downlink PVID intercepts issue when they are different.
- Fixed GWN menu "Error received: -16".
- Fixed the network card status switches multiple times after first pairing.
- Fixed client not getting any IP when the configured VLAN ID is set to 2.
- Fixed RE slow issue when connected to it, also fixed the RE disconnected issue when acquiring IP.
- Fixed physical port VLAN tag does not work issue.
- Fixed wrong LED test light status issue.
- Fixed 5G TX power test failed issue.
- Fixed AP CPU temperature consistently display as 20°C issue.
- Fixed "5G channel automatically switched from 6 to 161" prompt issue when switching SSID from dual to 5G.
- Fixed not receiving alarm notification after changing alarm setting frequently.
- Fixed AP not responding to cloud after receiving the distributed configuration.
- Fixed the alert settings "AP channel automatically switched" should not contain channel 0 issue.
- Fixed the password authenticate fails when set above 11 digits.
- Fixed DHCP relay feature unusable when switched the primary device.
- Fixed the voucher status displayed issue.
- Fixed unable to kick out the terminal connected to slave issue.
- Fixed the LED light turns on too slow issue after powering up.
- Fixed AP keeps rebooting when there are too many SSIDs in the environment.
- Fixed slave AP reboot and generate panic core issue.
- Fixed network loop occurs issue.
- Fixed secondary channel set lower than main channel but still displayed wrong in the AP channel list issue.
- Fixed devices automatically reboot when associated with 2.4G band.
- Fixed devices crash after receiving the configuration from the cloud.
- Fixed "Error" prompt when acquiring logs after adding devices onto cloud.
- Fixed Honeywell thermostats not connecting issue.
- Fixed the wireless device cannot obtain IP address issue when enabling DHCP service.

NEW FEATURE OVERVIEW

- **Added support for custom Channel on 2.4G band.**

This feature will allow admins to customize the desired channel on the 2.4G band.

Web UI:

Access Points → Configuration → Device Configuration

✕

Device Configuration

PVID ?

Allowed VLAN(s) ?

2.4G (802.11b/g/n)

Disable 2.4GHz ? ☐

Channel Width ?

Channel ?

Radio Power ?

Enable Minimum RSSI ?

Minimum Access Rate Limit ?

5G (802.11a/n/ac)

Disable 5GHz ? ☐

Channel Width ?

Channel ?

Save
Cancel

On GWN Cloud:

Settings → Wi-Fi → Global Radio Settings → 2.4G

2.4G (802.11b/g/n/ax) ^

Channel Width ⓘ ☒ 20MHz ☐ 20MHz/40MHz ☐ 40MHz

Channel ⓘ

Custom Channel

Radio Power ⓘ

[5/31/2023] FIRMWARE VERSION 1.0.25.3

PRODUCT NAME

GWN7610 / GWN7600 / GWN7600LR / GWN7602 / GWN7615 / GWN7605 / GWN7605LR / GWN7630 / GWN7630LR / GWN7624 / GWN7625 / GWN7660 / GWN7660LR / GWN7664 / GWN7664LR

DATE

05/31/2023

FIRMWARE FILE INFORMATION

- GWN7610 Firmware file name: gwn7610fw.bin
MD5 checksum: b537c0193a921ec369d51b958a7fb417
- GWN7600/GWN7600LR Firmware file name: gwn7600fw.bin
MD5 checksum: 5e12bb0a9d1b160b35955ed024c0c8af
- GWN7602 Firmware file name: gwn7602fw.bin
MD5 checksum: 2afd0759f076f67eb0f5be2258fc74af
- GWN7615 Firmware file name: gwn7615fw.bin
MD5 checksum: 17ccd9bfe20ffc54bf3a2b0e5ac23a0
- GWN7605/GWN7605LR Firmware file name: gwn7605fw.bin
MD5 checksum: 0d5660527e6353f943ae0f212b1b5906
- GWN7630/GWN7630LR Firmware file name: gwn7630fw.bin
MD5 checksum: b005676e3c31e0bdc8f53425e3d0f20b
- GWN7624 Firmware file name: gwn7624fw.bin
MD5 checksum: af997b13f92c0af571c01d2b2e721101
- GWN7625 Firmware file name: gwn7625fw.bin
MD5 checksum: 9234246b4ad6ce4c0234a3c11a451c47
- GWN7660/GWN7660LR Firmware file name: gwn7660fw.bin
MD5 checksum: a220521f75e544b7d479ad48804f9bcd
- GWN7664/GWN7664LR Firmware file name: gwn7664fw.bin
MD5 checksum: 1df6bb2931daf98c54b48509b8009498

CHANGES/ENHANCEMENT

- Fixed an issue causing MESH network instability on 1.0.25.1
- Internal bug fixes

[5/19/2023] FIRMWARE VERSION 1.0.25.1

PRODUCT NAME

GWN7610 / GWN7600 / GWN7600LR / GWN7602 / GWN7615 / GWN7605 / GWN7605LR / GWN7630 / GWN7630LR / GWN7624 / GWN7625 / GWN7660 / GWN7660LR / GWN7664 / GWN7664LR

DATE

05/19/2023

FIRMWARE FILE INFORMATION

- GWN7610 Firmware file name: gwn7610fw.bin
MD5 checksum: 7be6d53630b02ab90b8daf7019fa8329
- GWN7600/GWN7600LR Firmware file name: gwn7600fw.bin
MD5 checksum: 4828df4265afec3ca5d06ea293d252cb
- GWN7602 Firmware file name: gwn7602fw.bin
MD5 checksum: 43fc481888a77dafb6e19bb9ca570c43
- GWN7615 Firmware file name: gwn7615fw.bin
MD5 checksum: 542a6f934f302301e9e30a627714ec40
- GWN7605/GWN7605LR Firmware file name: gwn7605fw.bin
MD5 checksum: e613606708acaacae3df33322a257728
- GWN7630/GWN7630LR Firmware file name: gwn7630fw.bin
MD5 checksum: d8ba45c592334a6c10142abd5f707722
- GWN7624 Firmware file name: gwn7624fw.bin
MD5 checksum: ab1d976357677d37919349e0dd0698d5
- GWN7625 Firmware file name: gwn7625fw.bin
MD5 checksum: 77a02793fa7ae8020b803ecd69ae84dd
- GWN7660/GWN7660LR Firmware file name: gwn7660fw.bin
MD5 checksum: eb7fa9265e68c43d2db3764c5fe56007
- GWN7664/GWN7664LR Firmware file name: gwn7664fw.bin
MD5 checksum: 4ffdbbf22c9a749c45247e3e83bcd1b8

CHANGES/ENHANCEMENT

- Added support of IPv6 ND defense
- Added support of ARP defense
- Added support of disabling ethernet port
- Added support of switching RF timer
- Added support of DHCP relay and option82
- Added support of web packet capture saving to local PC
- Added support of trunk/access mode for NET/PoE port
- Added support of External syslog protocol selection

- Added support of Captive Portal - Active Directory Auth (LDAP)
- Added support of Captive Portal - kickout timeout unauthenticated clients
- Added support of Captive Portal - Daily access limit by auth method
- Added support of collecting logs by MAC
- Optimized client steering
- Internal bug fixes
-